



*Electricity Act 1994*

# **Electricity Regulation 2006**

**Current as at 27 October 2017**





Queensland

# Electricity Regulation 2006

## Contents

---

		Page
<b>Chapter 1</b>	<b>Preliminary</b>	
1	Short title . . . . .	11
2	Commencement . . . . .	11
3	Definitions . . . . .	11
4	Purposes . . . . .	11
5	How purposes are to be achieved . . . . .	12
6	Words have the same meaning as in wiring rules . . . . .	12
7	Way of describing electrical articles and appliances . . . . .	12
<b>Chapter 2</b>	<b>Technical requirements</b>	
<b>Part 1</b>	<b>Preliminary</b>	
8	Application of ch 2 . . . . .	13
<b>Part 2</b>	<b>Design, building and maintenance of electric lines and works</b>	
<b>Division 1</b>	<b>Compliance with part</b>	
9	Compliance with this part . . . . .	14
<b>Division 2</b>	<b>Earthing, frequency and voltage</b>	
10	Systems of earthing . . . . .	14
11	Supply at low voltage . . . . .	14
12	Supply at high voltage . . . . .	15
13	Changes of voltage at customer's consumers terminals . . . . .	15
<b>Division 3</b>	<b>Service lines</b>	
14	Service lines on customer's premises—electricity entity's obligations . . . . .	17
15	Service lines on customer's premises—customer's obligations . . . . .	18
<b>Division 4</b>	<b>Maintenance of works</b>	
16	Maintenance of works . . . . .	19
17	Clearing, lopping and pruning of trees on non-freehold land . . . . .	19
<b>Division 5</b>	<b>Works on publicly controlled places</b>	
18	Notice to be given to public entity . . . . .	20

Contents

---

19	Electricity entity must comply with public entity's requirements .	21
20	Guarding of work on publicly controlled place . . . . .	21
21	Restoration of publicly controlled place . . . . .	21
22	Electricity entity to keep publicly controlled place in good repair after work . . . . .	22
23	Warning signs on roads . . . . .	22
<b>Part 3</b>	<b>Customers' electrical installations</b>	
24	Installation and operation of electric line beyond person's property	23
25	Power factor . . . . .	24
26	Prevention of interference by motor installations and associated starting devices . . . . .	24
27	Interference with supply of electricity . . . . .	24
28	Customer's generating plant for interconnection to supply network	25
29	Requirement for circuit-breaker . . . . .	25
30	Coordination of customer's protection devices with electricity entity's protection system . . . . .	25
<b>Part 4</b>	<b>Qualifying customers' small photovoltaic generators</b>	
30AA	Prescribed credit amount for credit for electricity produced by small photovoltaic generators . . . . .	26
30AB	When a qualifying customer stops being entitled to be credited with prescribed credit amount for a category 1 qualifying customer . .	26
<b>Chapter 3</b>	<b>Electricity supply and sale to customers</b>	
<b>Part 1</b>	<b>Distribution entities</b>	
<b>Division 1</b>	<b>Obligations of distribution entities and customers</b>	
36	Regulating customer's use etc. of electricity . . . . .	27
37	Action if notice not complied with . . . . .	28
<b>Division 2</b>	<b>Meter and control apparatus requirements for premises</b>	
38	Application of div 2 . . . . .	29
39	Who is the responsible person . . . . .	29
40	Customer to change electrical installation for meter connection .	29
41	Customer to provide links connecting meter to incoming supply	29
42	No breaking or interfering with meter seal . . . . .	30
43	No breaking or interfering with control apparatus seal . . . . .	30
44	Placing meter or control apparatus on customer's premises . . .	30
45	Change of placement if building changes or works . . . . .	31
46	Customers to provide safe access . . . . .	31
<b>Division 3</b>	<b>Substations on customers' premises</b>	

57	Application of div 3 .....	32
58	Meaning of owner in div 3 .....	32
59	Owner to provide space for substation .....	33
60	Supply to other customers from substation .....	34
61	Limitation of compensation .....	34
62	Taking away distribution entity's equipment .....	35
<b>Part 4</b>	<b>Disputes about what is fair and reasonable</b>	
88	Dispute resolution .....	35
89	QCA may seek advice or information .....	36
90	Parties to maintain secrecy of advice or information .....	37
<b>Part 6</b>	<b>Electricity restrictions</b>	
<b>Division 1</b>	<b>Preliminary</b>	
92	Purpose of pt 6 .....	37
<b>Division 2</b>	<b>Restrictions in Ergon Energy distribution area</b>	
93	Where restrictions apply .....	38
94	Restrictions .....	38
<b>Chapter 4</b>	<b>Market and system arrangements</b>	
<b>Part 1</b>	<b>System and network control</b>	
<b>Division 1</b>	<b>Operating electrical installations</b>	
118	National Electricity Rules to be followed .....	40
<b>Division 2</b>	<b>Network control</b>	
119	Network operation not to interfere with Queensland system . . . .	40
120	National Electricity Rules to be followed .....	41
121	Dealings to be impartial .....	41
122	Confidentiality .....	41
123	Reasonable charges for services .....	42
<b>Part 2</b>	<b>Conditions of authorities and special approvals</b>	
<b>Division 1</b>	<b>General provisions</b>	
124	Separation of distribution and retail sectors .....	42
125	Compliance with National Electricity Rules instruments .....	42
127	Prescribed special approval holder—Act, s 61B .....	42
<b>Division 2</b>	<b>Demand management plans</b>	
127A	Definitions for div 2 .....	43
127B	Condition of distribution authority .....	43
127C	Preparing demand management plan .....	43
127D	Approving demand management plan .....	44

Contents

---

127E	Recommendations by regulator . . . . .	44
127F	Amending approved demand management plan . . . . .	45
127G	Complying with approved demand management plan . . . . .	45
127H	Reporting requirements . . . . .	46
<b>Part 3</b>	<b>Special approvals</b>	
128	Approval to connect for generation plant of particular State electricity entities installed immediately before 1 January 1995 . . . . .	46
129	Approval to connect for mobile generating plant for emergency or maintenance work by distribution entities . . . . .	46
130	Approval to connect particular generating plant with 30MW or less capacity . . . . .	47
131	Special approval holders treated as electricity entities—Act, s 59(2)	47
132	Special approval for QETC . . . . .	47
<b>Chapter 5</b>	<b>Prohibited interests</b>	
133	Distribution authorities . . . . .	47
<b>Chapter 7</b>	<b>Energy efficiency and performance of electrical equipment</b>	
<b>Part 1</b>	<b>Minimum energy efficiency and performance</b>	
<b>Division 1</b>	<b>Registration</b>	
138	Application for registration . . . . .	48
139	Requirements for registration . . . . .	49
140	Minimum energy efficiency and performance criteria . . . . .	50
141	Steps after registration . . . . .	50
142	Term of registration . . . . .	51
143	Change of name or address . . . . .	51
144	Changing energy efficiency label identifying electrical equipment	51
145	Refusal to change energy efficiency label . . . . .	52
146	Notice of change to energy efficiency label . . . . .	52
146A	Request for documents or information confirming compliance with relevant standard . . . . .	52
<b>Division 2</b>	<b>Transfer and cancellation of registration</b>	
147	Transfer of registration . . . . .	53
148	Notice of transfer . . . . .	53
149	Cancellation of registration . . . . .	53
150	Procedure before cancellation . . . . .	54
151	Notice, by holder, of cancellation of registration . . . . .	55
<b>Division 3</b>	<b>Energy efficiency label</b>	
152	Energy efficiency label . . . . .	55

<b>Division 4</b>	<b>Register</b>	
153	Register . . . . .	56
154	Inspection of register . . . . .	56
<b>Part 2</b>	<b>Testing and test reports</b>	
<b>Division 1</b>	<b>Preliminary</b>	
155	Testing of prescribed electrical equipment . . . . .	57
156	Test reports . . . . .	57
<b>Division 2</b>	<b>Check testing</b>	
157	Requirement by regulator to make available prescribed electrical equipment for testing . . . . .	58
158	What happens if check testing shows noncompliance . . . . .	58
159	What happens if check testing shows compliance . . . . .	59
160	Return of equipment made available to the regulator . . . . .	59
<b>Part 3</b>	<b>Offences</b>	
161	Part does not apply to second-hand prescribed electrical equipment	60
162	Prescribed electrical equipment in sch 4, pt 1—labelling and registration	60
163	Prescribed electrical equipment in sch 4, pt 2—registration . . . . .	62
164	Prescribed electrical equipment in sch 4, pt 3—registration . . . . .	62
165	Representations about 3-phase cage induction motors . . . . .	63
165A	Representations about digital television set-top boxes . . . . .	63
165B	Representations about external power supplies . . . . .	64
166	Marking and labelling particular fluorescent lamp ballasts . . . . .	64
<b>Chapter 8</b>	<b>Employment in government owned electricity industry</b>	
<b>Part 1</b>	<b>Preliminary</b>	
167	Definitions for ch 8 . . . . .	65
168	Meaning of redundant and redundant employee . . . . .	65
169	Meaning of suitable alternative employment . . . . .	66
170	Industrial Relations Commission may decide particular matters . . . . .	67
<b>Part 2</b>	<b>General employment conditions and entitlements</b>	
171	Definitions for pt 2 . . . . .	68
172	EGTS award is binding . . . . .	68
173	Secondment does not affect employment in the GOE industry . . . . .	68
174	Continuous service . . . . .	68
175	Calculation at a proportionate rate for particular employee . . . . .	69
176	Chapter 8 prevails over industrial instruments . . . . .	69

Contents

---

<b>Part 3</b>	<b>Transfer of employment within GOE industry</b>	
177	Application of pt 3 . . . . .	69
178	When there is transfer of employment within GOE industry . . . .	69
179	When employment with former employer and new employer is taken to be continuous service . . . . .	70
180	Transferred employee may elect for leave entitlement to become leave entitlement with new employer . . . . .	70
181	Payment by former employer to new employer towards long service leave entitlements not accrued on transfer . . . . .	71
182	Transferred employees not made redundant . . . . .	71
183	Particular new employers must pay superannuation into transferred employee's existing scheme . . . . .	72
<b>Part 4</b>	<b>Recognition of previous service other than on transfer</b>	
184	Application of pt 4 . . . . .	72
185	Recognition of previous service . . . . .	73
<b>Part 5</b>	<b>Long service leave</b>	
<b>Division 1</b>	<b>Entitlement</b>	
<b>Subdivision 1</b>	<b>General entitlement provision</b>	
186	Entitlement to long service leave . . . . .	74
<b>Subdivision 2</b>	<b>Service and continuity of service</b>	
187	Service recognised for long service leave purposes . . . . .	75
188	Casual employees . . . . .	75
189	Periods of absence without pay that count as service . . . . .	76
<b>Subdivision 3</b>	<b>Calculation of entitlement</b>	
190	Calculation of long service leave . . . . .	77
191	Casual employees—conversion to full-time equivalent . . . . .	77
<b>Division 2</b>	<b>Obtaining long service leave</b>	
192	Application for long service leave . . . . .	78
193	Employer's right to refuse or defer long service leave . . . . .	78
<b>Division 3</b>	<b>Miscellaneous provisions</b>	
194	Minimum period . . . . .	79
195	Employer's right to recall an employee from leave . . . . .	79
196	Public holidays happening during long service leave . . . . .	79
197	Illness during long service leave . . . . .	79
198	Payment of cash equivalent of long service leave . . . . .	81
199	Preservation of particular existing rights . . . . .	81
<b>Part 6</b>	<b>Locality allowances</b>	

200	Application of pt 6 .....	82
201	Allowance payable to a GOE industry employee with a dependent spouse or dependent child .....	83
202	Allowance payable to other employees .....	83
203	Allowance payable if both spouses are entitled .....	84
204	Allowance payable to an employee absent from headquarters on duty 84	
205	Allowance payable to an employee on leave .....	84
206	Building projects where site allowance is paid .....	85
<b>Part 7</b>	<b>Overtime payments</b>	
207	Overtime payments .....	85
<b>Chapter 9</b>	<b>Internal and external reviews</b>	
<b>Part 1</b>	<b>Review of decisions</b>	
208	Who may apply for internal review etc. ....	86
209	Applying for internal review .....	86
210	Stay of operation of decision etc. ....	86
211	Decision on internal review .....	87
<b>Part 2</b>	<b>Appeals and external review</b>	
<b>Division 1</b>	<b>External reviews by QCAT</b>	
212	Who may apply for external review .....	88
<b>Division 2</b>	<b>Appeals about recognition of previous service</b>	
214	Who may appeal .....	88
215	Making appeals .....	88
216	Starting appeals .....	89
217	Stay of operation of decisions .....	89
218	Powers of court on appeal .....	89
219	Effect of court's decision on appeal .....	90
220	Procedure of court .....	90
221	Appeals .....	90
<b>Chapter 10</b>	<b>General provisions</b>	
<b>Part 1</b>	<b>Application of Judicial Review Act to State electricity entities</b>	
222	Commercial and excluded activities for Act, s 256 .....	91
<b>Part 1A</b>	<b>Distribution network code provisions</b>	
<b>Division 1</b>	<b>Proposals to amend</b>	
222A	Proposal to amend .....	92
222B	QCA response to proposal .....	92

Contents

---

222C	Notice of decision not to submit for consultation . . . . .	92
222D	QCA-initiated amendments not affected . . . . .	93
<b>Division 2</b>	<b>Required consultation for QCA making or amending distribution network code</b>	
<b>Subdivision 1</b>	<b>Preliminary</b>	
222E	Prescribed consultation—Act, ss 120H(2) and 120PA(1) . . . . .	93
222F	Application of div 2 for amendments . . . . .	93
<b>Subdivision 2</b>	<b>Interim steps</b>	
222G	Application of sdiv 2 . . . . .	94
222H	Interim consultation notice . . . . .	94
222I	Submissions . . . . .	95
222J	Considering submissions . . . . .	95
222K	Release of draft report and draft proposed code . . . . .	95
<b>Subdivision 3</b>	<b>Final steps</b>	
222L	Final consultation notice . . . . .	95
222M	Submissions . . . . .	96
222N	Considering submissions . . . . .	96
222O	Release of final report and final proposed code . . . . .	96
<b>Part 2</b>	<b>Declared State electricity entities</b>	
224	Declarations—Act, s 259A(2) . . . . .	97
<b>Part 3</b>	<b>Miscellaneous</b>	
225	Approved industry superannuation scheme . . . . .	97
225A	Prescribed amount—small photovoltaic generator connected at particular premises . . . . .	98
226	Fees . . . . .	98
227	Forms . . . . .	98
<b>Part 4</b>	<b>Transitional provisions</b>	
<b>Division 1</b>	<b>Transitional provisions for original regulation</b>	
228	Definition for div 1 . . . . .	99
229	Continuation of agreements for substations . . . . .	99
230	Electric lines installed or operated before 1 October 2002 . . . . .	99
231	Existing registrations of items of prescribed electrical equipment . . . . .	99
232	Existing approvals, notices, decisions, directions and requirements under 1994 regulation . . . . .	100
233	Existing applications . . . . .	100
234	Unfinished appeals . . . . .	100
<b>Division 2</b>	<b>Transitional provisions for Electricity Amendment Regulation (No.</b>	

---

	<b>3) 2007</b>	
235	Small customers for negotiated retail contracts under Act, s 312	101
236	Existing decisions under s 88 or 211	101
237	Unfinished referrals and reviews	101
238	Contestable customers for National Electricity Rules	102
<b>Division 3</b>	<b>Transitional provision for Electricity Amendment Regulation (No. 4) 2007</b>	
239	Provision for new s 142	102
<b>Division 4</b>	<b>Transitional provision for Electricity Amendment Regulation (No. 1) 2009</b>	
240	Demand management plans for 2009 financial year	103
<b>Schedule 1</b>	<b>Maximum permitted rating of electric motors</b>	104
<b>Schedule 3</b>	<b>Special approval holders treated as electricity entities</b>	106
<b>Schedule 4</b>	<b>Prescribed electrical equipment and relevant standards</b>	107
<b>Schedule 5</b>	<b>QCA review of decisions</b>	113
<b>Schedule 6</b>	<b>External reviews of administrative decisions by QCAT</b>	115
<b>Schedule 7</b>	<b>Fees payable to regulator</b>	116
<b>Schedule 8</b>	<b>Maximum fees payable to electricity entity</b>	117
<b>Schedule 9</b>	<b>Dictionary</b>	120



---

# Electricity Regulation 2006

## Chapter 1 Preliminary

### 1 Short title

This regulation may be cited as the *Electricity Regulation 2006*.

### 2 Commencement

This regulation commences on 1 September 2006.

### 3 Definitions

The dictionary in schedule 9 defines particular words used in this regulation.

### 4 Purposes

The main purposes of this regulation are to—

- (a) ensure a secure, efficient and economic supply of electricity to customers on fair and reasonable terms; and
- (b) ensure customers' interests are adequately protected; and
- (c) provide for the proper measurement of the energy efficiency and performance of electrical equipment; and
- (d) inform the public about the energy efficiency and performance of electrical equipment; and
- (e) prescribe particular conditions of employment for employees in the GOE industry.

## **5 How purposes are to be achieved**

The purposes of this regulation are to be achieved mainly by—

- (a) prescribing standards and procedures for the design, building and maintenance of electric lines and works; and
- (d) prescribing standards and procedures for measuring energy efficiency and the performance of electrical equipment; and
- (e) providing for the registration and labelling of electrical equipment; and
- (f) providing for continuity of service for leave purposes for employees transferring within the GOE industry; and
- (g) providing for long service leave and locality allowance entitlements for GOE industry employees; and
- (h) providing for award conditions and entitlements of employment for State electricity entities and their electricity industry employees.

## **6 Words have the same meaning as in wiring rules**

- (1) Words and expressions used in the wiring rules have the same respective meanings in this regulation.
- (2) However, for this regulation, the expression ‘point of supply’ in the wiring rules has the same meaning as ‘consumers terminals’ has in this regulation.

## **7 Way of describing electrical articles and appliances**

An electrical article or appliance or type of electrical article or appliance may be described by reference to its model or in any other way.

---

## Chapter 2      Technical requirements

### Part 1              Preliminary

#### 8              Application of ch 2

- (1) This chapter does not apply to—
- (a) an electric line or works within the limits of a mine; or
  - (b) petroleum plant.

- (2) In this section—

***mine*** means—

- (a) a coal mine within the meaning of the *Coal Mining Safety and Health Act 1999*; or
- (b) a mine within the meaning of the *Mining and Quarrying Safety and Health Act 1999*.

***petroleum plant*** means private plant or an electrical installation, subject to inspection under the *Petroleum and Gas (Production and Safety) Act 2004*.

***private plant*** means generating plant not used by an electricity entity or special approval holder in accordance with an authority or special approval.

## **Part 2                      Design, building and    maintenance of electric lines    and works**

### **Division 1                Compliance with part**

#### **9                      Compliance with this part**

A person who designs, builds, maintains or operates an electric line or works must ensure the provisions of this part relevant to the line or works are complied with.

Maximum penalty—20 penalty units.

### **Division 2                Earthing, frequency and voltage**

#### **10                    Systems of earthing**

The system of earthing used by an electricity entity for low voltage supply to customers must be the multiple earthed neutral system, or, if that system is not effective, another suitable system that complies with the wiring rules.

#### **11                    Supply at low voltage**

- (1) Electricity for general supply must be alternating current having a nominal frequency of 50Hz.
- (2) The standard voltage for the supply, before 27 October 2018, of electricity at low voltage from a 3-phase system is—
  - (a) between a phase conductor and a neutral conductor—
    - (i) the nominal voltage stated for the system in AS 60038; or
    - (ii) 240V; and
  - (b) between 2 phase conductors—

- (i) the nominal voltage stated for the system in AS 60038; or
  - (ii) 415V.
- (3) The standard voltage for the supply, before 27 October 2018, of electricity at low voltage from a single phase system is—
  - (a) between a phase conductor and a neutral conductor—
    - (i) the nominal voltage stated for the system in AS 60038; or
    - (ii) 240V; and
  - (b) between the phase conductors—
    - (i) the nominal voltage stated for the system in AS 60038; or
    - (ii) 480V.
- (4) The standard voltage for the supply, on or after 27 October 2018, of electricity at low voltage from a 3-phase system or a single phase system is the nominal voltage stated for the system in AS 60038.

## **12 Supply at high voltage**

If an electricity entity agrees with a customer to supply electricity to the customer at high voltage, the agreed voltage is the standard voltage for the supply.

## **13 Changes of voltage at customer's consumers terminals**

- (1) Supply of electricity by an electricity entity to a customer must be maintained at the standard voltage for the supply mentioned in section 11 or 12.
- (2) For the supply of electricity at low voltage before 27 October 2018, the supply is taken to be maintained at the standard voltage for the supply if the voltage at a customer's consumers terminals—

[s 13]

---

- (a) for the standard voltage mentioned in section 11(2)(a)(i) or (b)(i) or (3)(a)(i) or (b)(i)—does not differ from the standard voltage by more than the percentage stated for the supply voltage range in AS 60038; or
  - (b) for the standard voltage mentioned in section 11(2)(a)(ii) or (b)(ii) or (3)(a)(ii) or (b)(ii)—is no more than 6% more or less than the standard voltage.
- (3) For the supply of electricity at low voltage on or after 27 October 2018, the supply is taken to be maintained at the standard voltage for the supply if the voltage at a customer's consumers terminals—
- (a) for supply before 1 July 2020—does not differ from the standard voltage by more than the percentage stated for the supply voltage range in AS 60038; or
  - (b) otherwise—
    - (i) is within the minimum preferred steady state median voltage and the maximum preferred steady state median voltage stated in AS 61000; or
    - (ii) if the voltage can not be maintained under subparagraph (i)—does not differ from the standard voltage by more than the percentage stated for the supply voltage range in AS 60038.
- (4) The supply of electricity at high voltage is taken to be maintained at the standard voltage for the supply if the voltage at a customer's consumers terminals is—
- (a) for the supply of electricity at a voltage of 22,000V or less—no more than 5% more or less than the standard voltage; or
  - (b) for the supply of electricity at a voltage more than 22,000V—within the margin agreed between the electricity entity and the customer.
- (5) For measuring the voltage at a customer's consumers terminals for subsection (2), (3) or (4), the methodology for the measurement of steady state voltage stated in AS 61000 must be used.

(6) In this section—

*AS 61000* means AS 61000.3.100 (Limits—Steady state voltage limits in public electricity systems) as in force from time to time.

## **Division 3                      Service lines**

### **14      Service lines on customer's premises—electricity entity's obligations**

- (1) An electricity entity must, in accordance with recognised practice in the electricity industry—
  - (a) decide the route, termination point, number of phases, lengths, type and size of its service lines; and
  - (b) provide and install or arrange for the provision and installation of its service lines.
- (2) The electricity entity must—
  - (a) if requested by a customer to connect a service line that is a standard control service—meet the cost of providing and installing the service line to the customer's premises; or
  - (b) if requested by a customer to provide and install or arrange for the provision and installation of a service line that is not a standard control service—provide and install or arrange for the provision and installation of the service line to the customer's premises at the customer's expense.
- (3) However, the maximum length of a service line required to be provided and installed within a customer's premises by an electricity entity at the electricity entity's cost is—
  - (a) 20m for an overhead service line; or
  - (b) 7m for an underground service line.
- (4) Also, subsections (1)(b), (2)(a) and (3) apply only to the provision and installation of 1 initial service line that is a

standard control service at particular premises, whether before or after the commencement of this section.

*Example—*

Subsection (1)(b) does not apply if a customer requires an additional service line, or the upgrading of the existing service line, at the customer's premises to operate 3-phase air-conditioning equipment.

- (5) For subsections (1) and (3), a service line must be measured from the customer's property alignment or, if the line does not cross the property alignment, the point of origin of the service line.

## **15 Service lines on customer's premises—customer's obligations**

- (1) A customer must provide and maintain, free of cost to an electricity entity, the facilities the entity reasonably decides are necessary to attach an overhead service line to the customer's premises or for the entrance, support, protection and termination of an underground service line.

*Examples of facilities that may be provided by a customer—*

- a service riser bracket
  - timber backing for the electricity entity's 'J' hook
- (2) The customer must provide access for the entity to install, test, maintain or take away its service line without hindrance or obstruction.
- (3) The customer must pay the reasonable cost of a service line provided, unless—
- (a) the service line is a standard control service; and
  - (b) the line is an initial service line to the customer's premises.

---

## Division 4                      Maintenance of works

### 16            Maintenance of works

An electricity entity must, in accordance with recognised practice in the electricity industry, periodically inspect and maintain its works to ensure the works remain in good working order and condition.

### 17            Clearing, lopping and pruning of trees on non-freehold land

- (1) An electricity entity may clear, lop or prune trees growing on non-freehold land if—
  - (a) it is necessary to do so to build, maintain or operate an electric line or works on the land; and
  - (b) the entity holds the benefit of an easement, licence or other agreement in relation to the line or works.
- (2) Subsection (1) applies—
  - (a) whether or not the easement, licence or agreement authorises the clearing, lopping or pruning; and
  - (b) subject to—
    - (i) the conditions of the easement, licence or agreement; and
    - (ii) section 18.
- (3) To the extent a local planning instrument or a local law is inconsistent with subsection (1), the local planning instrument or local law is of no effect.

- (4) In this section—

***local planning instrument*** means a local planning instrument under the *Planning Act 2016*.

***trees*** see the *Forestry Act 1959*.

## **Division 5                      Works on publicly controlled places**

### **18        Notice to be given to public entity**

- (1) This section applies if an electricity entity intends to take action mentioned in subsection (2) in a publicly controlled place unless—
  - (a) the action is an action authorised under sections 140 to 141 of the Act; and
  - (b) the entity complies with the section in relation to the entry to the place and the taking of the action.
- (2) The action is—
  - (a) opening or breaking up the soil or pavement of the place; or
  - (b) clearing, lopping or pruning a tree or other vegetation growing in or over the place, other than for routine maintenance; or
  - (c) opening or breaking up a sewer, drain or tunnel in or under the place; or
  - (d) temporarily stopping or diverting traffic on or from the place; or
  - (e) building a drain, excavation, subway or tunnel in or under the place.
- (3) The electricity entity must give at least 14 days written or oral notice of its intention to the public entity that has control of the publicly controlled place unless the notice is given in accordance with another period of notice agreed between the entities.
- (4) However, subsection (5) applies if, in the electricity entity's opinion, there is an emergency in which—
  - (a) there is an actual or a potential danger to persons or property; or
  - (b) the supply of electricity to a customer has been interrupted.

- (5) If this subsection applies, the electricity entity may act under section 101 of the Act to remedy a defect, eliminate an actual or potential danger or restore the supply of electricity to a customer, without first giving the notice under subsection (3).
- (6) If the electricity entity acts under subsection (5), it must give the notice mentioned in subsection (3) as soon as practicable.

## **19 Electricity entity must comply with public entity's requirements**

- (1) If an electricity entity goes on a publicly controlled place to take action for which notice must be given under section 18, the public entity that has control of the place may require the electricity entity to act on the days and at the times the public entity reasonably requires.
- (2) The electricity entity must comply with a reasonable requirement by the public entity under subsection (1).

## **20 Guarding of work on publicly controlled place**

- (1) An electricity entity that has opened or broken up a publicly controlled place must, at all times while the place is opened or broken up, ensure—
  - (a) it is barricaded and guarded; and
  - (b) signs and lights sufficient for the warning and guidance of traffic, including pedestrians, are set up and maintained against or near the place where it is opened or broken up.
- (2) If required by the public entity, the electricity entity must also set up and maintain additional warning or protection devices to safeguard the public whether before or during the work.

## **21 Restoration of publicly controlled place**

- (1) An electricity entity that has opened or broken up a publicly controlled place must—

[s 22]

---

- (a) with all convenient speed, finish the work; and
  - (b) on finishing the work, take away from the place all plant, materials and equipment not built into the work; and
  - (c) restore, as far as practicable, the place where the work was carried out and leave it tidy.
- (2) The way action under subsection (1) is to be carried out by or for the electricity entity is as agreed between the electricity entity and the public entity controlling the place and in accordance with reasonable conditions and requirements stated by the public entity.

## **22 Electricity entity to keep publicly controlled place in good repair after work**

- (1) An electricity entity must keep a publicly controlled place that has been opened or broken up and restored by it in good repair—
- (a) for 3 months after restoring the place; and
  - (b) if the ground subsides and continues to subside—for up to a further 9 months.
- (2) The way maintenance work is to be carried out by or for the electricity entity is as agreed between the electricity entity and the public entity that controls the place.

## **23 Warning signs on roads**

If an electricity entity or its contractor is building or maintaining an electric line or other works on a road, signs and lights set up and maintained by the entity and its contractor to safeguard the public must be the appropriate official traffic signs under the *Transport Operations (Road Use Management) Act 1995*.



[s 25]

---

- (5) The regulator must give the person a QCAT information notice about the decision to give the direction.
- (6) If the person does not comply with the direction, the regulator may take away the electric line and recover the cost of the removal from the person as a debt payable to the State.
- (7) A person who complies with subsections (1) to (3) about an electric line does not need an authority or special approval under the Act to install or operate the line.

## **25 Power factor**

A customer must comply with any requirement of its supplier made of the customer under section 36 about the power factor of an electrical installation.

*Note—*

See section 37 for what action the distribution entity may take if the customer does not comply with the requirement.

## **26 Prevention of interference by motor installations and associated starting devices**

A person may connect a motor installation or associated starting device only if it is designed and operated to comply with any requirements of the regulator to prevent interference with supply of electricity to other customers.

*Note—*

See sections 36 and 37 for what action a distribution entity may take if the distribution entity considers the installation or device interferes, or is likely to interfere, with the supply of electricity to other customers.

## **27 Interference with supply of electricity**

A customer must not use electricity or an electrical article so the supply of electricity to other customers of the supplier who supplies the electricity is unreasonably interfered with.

*Note—*

See sections 36 and 37 for what action a distribution entity may take if the distribution entity considers the installation or device interferes, or is likely to interfere, with the supply of electricity to other customers.

**28 Customer's generating plant for interconnection to supply network**

- (1) A customer must not install generating plant for interconnection with a supplier's supply network without the supplier's agreement.

Maximum penalty—20 penalty units.

- (2) The agreement must include the conditions for securing safe and stable parallel operation of the supply network and the generating plant.

**29 Requirement for circuit-breaker**

- (1) If required by the relevant supplier, a customer must ensure the customer's electrical installation has a circuit-breaker as a main switch or a circuit-breaker instead of a fuse as part of the installation.

Maximum penalty—20 penalty units.

- (2) However, the customer may choose whether to have a circuit-breaker as a main switch or a circuit-breaker instead of a fuse if the relevant supplier does not state which is required.

**30 Coordination of customer's protection devices with electricity entity's protection system**

- (1) An electricity entity may cause the characteristics of a customer's protection device to be changed and tested to maintain discrimination between the customer's protection equipment and the electricity entity's protection system.
- (2) The electricity entity may seal the adjusted protection equipment.



- 
- (3) A qualifying customer also stops being entitled to be credited with the prescribed credit amount under section 44A(1)(b) of the Act for a category 1 qualifying customer if—
- (a) no qualifying generator has been connected at the qualifying customer's premises to a distribution entity's supply network by the end of 30 June 2013; or
  - (b) no qualifying generator is ready to be connected at the qualifying customer's premises to a distribution entity's supply network by the end of 30 June 2013.

## **Chapter 3      Electricity supply and sale to customers**

### **Part 1            Distribution entities**

#### **Division 1        Obligations of distribution entities and customers**

##### **36      Regulating customer's use etc. of electricity**

- (1) This section applies if, in the distribution entity's opinion—
- (a) the use or intended use of an electrical article by a customer unreasonably interferes, or is likely to unreasonably interfere, with the entity's supply of electricity to other customers; or
  - (b) a customer uses or deals with electricity so the supply of electricity to other customers is, or is likely to be, unreasonably interfered with; or
  - (c) a customer's motor installation or associated starting device interferes, or is likely to interfere, with supply of electricity to other customers; or

[s 37]

---

- (d) it is necessary to regulate the power factor of a customer's electrical installation.
- (2) The entity may, by written notice to the customer, require the customer to—
- (a) regulate the use of the electrical article; or
  - (b) use or deal with electricity supplied in a stated way; or
  - (c) ensure a motor installation or starting device connected to a source of electricity supply complies with the requirements of the regulator under section 26; or
  - (d) ensure the power factor of an electrical installation measured over any 30 minutes at the customer's consumers terminals—
    - (i) for low voltage supply to the customer—
      - (A) is at least 0.8 lagging; and
      - (B) is not a leading power factor unless the entity agrees; or
    - (ii) for high voltage supply to the customer—is within the range stated in the National Electricity Rules, schedule 5.3.5.
- Editor's note—*
- National Electricity Rules, schedule 5.3.5 (Power factor requirements)
- (3) The notice must state when it must be complied with.
  - (4) The notice must be accompanied by or include an information notice about the decision.

### **37 Action if notice not complied with**

If a customer does not comply with a notice under section 36, the distribution entity may—

- (a) refuse to provide customer connection services to the customer's electrical installation until the customer complies with the notice; or



- (b) the customer is making, or is proposing to make, a substantial change to the meter or a substantial change to the premises that relates to the meter.

*Examples—*

- relocation of the meter
- replacement of the mounting for the meter
- rewiring of the premises

- (3) The responsible person may seal the links.

#### **42 No breaking or interfering with meter seal**

- (1) This section applies if the responsible person has provided a meter or links for the premises and there is a seal on the meter or links.
- (2) A person (the *first person*) must not break or interfere with the seal unless the responsible person has permitted the first person to do so.

Maximum penalty—20 penalty units.

#### **43 No breaking or interfering with control apparatus seal**

- (1) This section applies if a distribution entity for the premises has provided control apparatus for the premises and there is a seal on the apparatus.
- (2) A person must not break or interfere with the seal unless the distribution entity has permitted the person to do so.

Maximum penalty—20 penalty units.

#### **44 Placing meter or control apparatus on customer's premises**

- (1) The customer must, at the customer's expense—
- (a) provide at the premises space, housing, mounting and connecting facilities for each meter and control

---

apparatus provided by the responsible person or distribution entity for the premises; and

- (b) maintain the facilities in a safe and sound condition.
- (2) The facilities must be in a position that meets the reasonable requirements of—
  - (a) for a meter—the responsible person; or
  - (b) for control apparatus—the distribution entity for the premises.

#### **45 Change of placement if building changes or works**

- (1) This section applies if, because of building changes or similar works, the position of a meter or control apparatus at the premises no longer meets requirements made under section 44(2).
- (2) The customer must, at the customer's expense—
  - (a) provide space, housing, mounting and connecting facilities in another position at the premises that meets the reasonable requirements of—
    - (i) for the meter—the responsible person; or
    - (ii) for control apparatus—the distribution entity for the premises; and
  - (b) arrange for relocation to the other position by—
    - (i) for the meter—the responsible person; or
    - (ii) for control apparatus—the distribution entity.

#### **46 Customers to provide safe access**

- (1) This section applies if the customer does not provide safe access at any reasonable time to read a meter and install, test, maintain or take away the supplier's works without hindrance or obstruction to—

[s 57]

---

- (a) the distribution entity for the premises, a special approval holder or the responsible person (the *relevant entity*); or
  - (b) an electricity officer of a relevant entity; or
  - (c) a person authorised by a relevant entity.
- (2) The relevant entity may, by written notice to the customer, require the customer to provide the access within a stated period of at least 1 month.
  - (3) If the customer does not comply with the notice, the relevant entity may install alternative metering or other equipment to enable consumption to be measured by remote or other suitable ways.
  - (4) Subsection (3) does not limit or otherwise affect another remedy the relevant entity has against the customer.
  - (5) The relevant entity may recover from the customer as a debt its costs reasonably incurred in acting under subsection (3).

## **Division 3                      Substations on customers' premises**

### **57            Application of div 3**

- (1) This division applies if the supply of electricity required by customers in premises is more than, or is reasonably estimated by the distribution entity to be more than, a total maximum demand of 100kV.A worked out under the wiring rules.
- (2) This division also applies to supply of electricity to customers in premises if the regulator, in special circumstances, approves its application.

### **58            Meaning of *owner* in div 3**

In this division—

---

*owner*, of premises, includes a person who is the proprietor, lessee or occupier of the premises or part of the premises.

## 59 Owner to provide space for substation

- (1) This section applies if, to meet an existing or likely demand for supply of electricity by customers who are, or in the future may be, in premises, the distribution entity reasonably considers it is necessary to install a substation on the premises.
- (2) The entity may require the owner of the premises to—
  - (a) provide, free of cost to the entity, the space for a substation; and
  - (b) give a right of way to the entity for its electric lines and cables to and from the substation; and
  - (c) provide to the entity, or persons authorised by it, access to the entity's equipment on the premises at all times to allow the entity to install, maintain or take away its equipment without hindrance or obstruction.
- (3) The owner must also provide permanent handling facilities, segregated access passageways or ventilating ducts if they are needed because of the location the owner proposes to provide for the substation.
- (4) An owner who provides space for a substation under this section must—
  - (a) maintain the floor or foundation, walls or enclosure, ceiling and access door of the space in sound condition; and
  - (b) repair damage to or deterioration of the space, other than damage or deterioration directly attributable to the use of the space by the entity.
- (5) Repairs must be done within the time and to the extent reasonably directed by the entity.
- (6) If the owner does not comply with subsection (4), the entity may—

- (a) do anything necessary to carry out the maintenance or repair; and
  - (b) recover from the owner as a debt the reasonable costs of anything done by the entity under paragraph (a).
- (7) In this section—
- space*, for a substation, means—
- (a) necessary or suitable floor or foundation, walls or enclosure, ceiling and access doors in the part of the premises where the substation is to be located and installed, with the walls or enclosure, ceiling and access doors being suitably painted; and
  - (b) necessary or suitable places for entry and exit of electric lines and cables for the substation; and
  - (c) if required by the distribution entity—suitable lighting and general power outlets.

## **60 Supply to other customers from substation**

- (1) A distribution entity may only use an electric line or equipment installed by it on premises under this division for providing customer connection services to customers outside the premises if the owner of the premises agrees.
- (2) If the agreement is given, it continues in force while the substation is still being used to supply electricity to the premises.
- (3) Subsection (2) applies even if the total maximum demand for the electricity is less than the amount mentioned in section 57(1).

## **61 Limitation of compensation**

Unless agreed between the owner and the distribution entity, an owner of premises for a substation is not entitled to compensation from the distribution entity for—

- (a) the installation of the substation; or

- (b) complying with a requirement under section 59; or
- (c) carrying out an obligation imposed on the owner under section 59; or
- (d) agreeing under section 60 for the substation to be used for the purpose of supplying customers outside the premises, other than reasonable compensation for any additional space, over and above the space used to supply customers on the premises, occupied by the substation for that purpose.

## **62 Taking away distribution entity's equipment**

- (1) If supply of electricity to an owner's premises is no longer needed, the distribution entity must, within a reasonable period, take away, at its own cost, its electric lines, cables and equipment from the premises if the owner asks.
- (2) Subsection (3) applies if the electric lines, cables and equipment are, under section 60, used to supply electricity to customers not on the premises.
- (3) In deciding what is a reasonable period for subsection (1), regard must be had to whether the period is enough to allow the distribution entity to provide an alternative supply of electricity to the customers mentioned in subsection (2).

## **Part 4 Disputes about what is fair and reasonable**

### **88 Dispute resolution**

- (1) This section applies if—
  - (a) the Act or this regulation requires an electricity entity to do something on—
    - (i) fair and reasonable terms; or
    - (ii) a fair and reasonable basis; and

[s 89]

---

- (b) there is a dispute about fairness or reasonableness; and
  - (c) the dispute is not—
    - (i) an access dispute under the *Queensland Competition Authority Act 1997*, section 112(2); or
    - (ii) a dispute that may be the subject of a dispute referral to the energy and water ombudsman under the *Energy and Water Ombudsman Act 2006*.
- (2) A party to the dispute may ask QCA to resolve the dispute.
  - (3) QCA may—
    - (a) give instructions about procedures the parties must follow to attempt to resolve the dispute before QCA takes steps to resolve it; or
    - (b) require a party to give QCA information QCA considers necessary to enable the dispute to be resolved.
  - (4) QCA must give each party a reasonable opportunity to make representations before making the decision.
  - (5) After considering any representations, QCA must decide the issue in dispute.
  - (6) QCA must give the parties a QCAT information notice about the decision.

## **89 QCA may seek advice or information**

- (1) This section applies if, under section 88(2), QCA has been asked to resolve a dispute.
- (2) To help resolve the dispute, QCA may seek advice or information from any other person.
- (3) QCA may take the advice or information into account in resolving the dispute.
- (4) If QCA seeks information or advice or takes into account advice or information QCA has been given for any other dispute, QCA must—

- (a) if the advice or information is written—give a copy of it to the parties; or
- (b) if the advice or information is oral—disclose the substance of the advice to the parties.

## **90 Parties to maintain secrecy of advice or information**

- (1) This section applies if under section 89(4) QCA gives advice or information, or discloses the substance of advice or information, to a person who is a party to the dispute.
- (2) The person must not disclose the advice or information to another person unless the person has a reasonable excuse.

Maximum penalty—20 penalty units.

- (3) It is a reasonable excuse for a person to disclose the advice or information if the disclosure is for—
  - (a) the resolution of the dispute; or
  - (b) an external review of QCA’s decision on the dispute.

# **Part 6 Electricity restrictions**

## **Division 1 Preliminary**

### **92 Purpose of pt 6**

The purpose of this part is ensure a regular, economically efficient and constant supply of electricity within the available supply capacity of particular supply networks, or parts of them.

## **Division 2                      Restrictions in Ergon Energy distribution area**

### **93        Where restrictions apply**

The electricity restrictions under section 94 apply to electricity supplied by Ergon Energy in the localities mentioned in schedule 1 through its supply network.

### **94        Restrictions**

(1) The use of the following electrical articles by customers is prohibited—

- (a) electric motors with a rating greater than—
  - (i) the rating stated for the relevant locality in schedule 1; and
  - (ii) if the motor is not installed and operated in accordance with the guidelines published by Ergon Energy—1.5kW;

*Editor's note—*

The guidelines are available from the Ergon Energy offices at 109 Lake Street, Cairns, 34–46 Dalrymple Road, Garbutt, Townsville and the corner of Fitzroy Street and Alma Street, Rockhampton.

- (b) instantaneous water heaters with a rating of more than 2.4kW;
  - (c) welding power sources.
- (2) Subsection (1) does not apply—
- (a) to the following welding power sources—
    - (i) 415V, 3-phase input light industrial welding power sources;
    - (ii) 250V, single-phase limited input welding power sources; or

- (b) to electric motors that are part of a public water supply system or a community sewerage system installed and operated in the way required by Ergon Energy; or
  - (c) to electrical articles at Mapoon installed before 1 December 1998; or
  - (d) if the customer satisfies Ergon Energy, by the written advice of a doctor, that a stated electrical article must be used to reduce a threat to a person's life.
- (3) In this section—

***instantaneous water heater*** means an instantaneous water heater described in—

- (a) AS/NZS 3350.2.35:1999—Safety of household and similar electrical appliances, part 2.35—Particular requirements— Instantaneous water heaters; or
- (b) AS/NZS 60335.2.35:2004—Household and similar electrical appliances—Safety, part 2.35—Particular requirements for instantaneous water heaters.

***welding power source*** means an electric arc welding power source that has—

- (a) a transformer for alternating current welding; or
- (b) a transformer-rectifier unit for direct current, or alternating current and direct current, welding.

## **Chapter 4      Market and system arrangements**

### **Part 1            System and network control**

#### **Division 1        Operating electrical installations**

##### **118      National Electricity Rules to be followed**

A person must comply with the National Electricity Rules in operating an electrical installation if the installation—

- (a) is connected directly to a transmission grid that is part of the Queensland system; or
- (b) is connected to a part of a supply network stated by AEMO or the System Operator for Queensland to be relevant to the security and reliability of the Queensland system; or
- (c) includes facilities for the provision of ancillary services stated by AEMO or the System Operator for Queensland to be relevant to the security and reliability or the economic operation of the Queensland system.

Maximum penalty—20 penalty units.

#### **Division 2        Network control**

##### **119      Network operation not to interfere with Queensland system**

- (1) A distribution entity must not operate its supply network in a way that interferes with the performance of the Queensland system without the agreement of AEMO or the System Operator for Queensland.

Maximum penalty—20 penalty units.

- (2) In this section—  
*operate* includes providing network control.

## **120 National Electricity Rules to be followed**

A person must comply with the National Electricity Rules in operating an electrical installation if the installation—

- (a) is connected directly to a supply network that is part of the Queensland system; or
- (b) includes facilities for the provision of ancillary services to the supply network.

Maximum penalty—20 penalty units.

## **121 Dealings to be impartial**

An electricity entity, in carrying out network control, must be impartial in its dealings with all other electricity entities, special approval holders and customers.

## **122 Confidentiality**

- (1) An electricity entity may publish or release to a person information acquired by the entity in carrying out network control, and that gives or is likely to give the person a material commercial advantage over anyone else, only if—
- (a) the giving of the information is for another lawful purpose; and
  - (b) any commercial advantage is only incidental to the purpose.
- (2) Subsection (1) does not apply to the giving to a person information about—
- (a) the person; or
  - (b) with another person's written permission, the other person.

### **123 Reasonable charges for services**

An electricity entity may charge customers for the reasonable cost of carrying out its network control functions.

## **Part 2 Conditions of authorities and special approvals**

### **Division 1 General provisions**

#### **124 Separation of distribution and retail sectors**

It is a condition of a distribution authority that its holder must not hold a retailer authorisation.

#### **125 Compliance with National Electricity Rules instruments**

- (1) This section applies to the holder of an authority or special approval if the holder is a Registered participant.
- (2) It is a condition of an authority or special approval that its holder must comply with any National Electricity Rules instrument applying to the activities authorised by the authority or special approval.
- (3) In this section—

*authority* means a generation authority, transmission authority or distribution authority.

*National Electricity Rules instrument* means a guideline, power system operating procedure or other procedure, protocol or standard made under the Rules.

#### **127 Prescribed special approval holder—Act, s 61B**

Essential Energy, in relation to special approval no. SA01/11, is prescribed for the Act, section 61B.

---

## Division 2                      Demand management plans

### 127A Definitions for div 2

In this division—

*approved demand management plan* means a demand management plan approved by the regulator under this division.

*demand management*, by a distribution entity, means any activity in which the entity is involved that reduces demand on the entity's supply network or part of the supply network.

*demand management plan*, for a financial year, means a plan for the year that complies with section 127C(2).

*strategy* see section 127C(2)(a).

### 127B Condition of distribution authority

It is a condition of a distribution authority that its holder must comply with this division.

### 127C Preparing demand management plan

- (1) A distribution entity must, for each financial year, prepare a demand management plan.
- (2) The distribution entity must include in the plan—
  - (a) the entity's long-term strategy for demand management (the *strategy*), including the following—
    - (i) the principles intended to guide the achievement of the strategy;
    - (ii) a description of existing and planned programs for demand management for the next 5 financial years;
    - (iii) any identified opportunities to achieve the strategy;

[s 127D]

---

- (b) the entity's proposed initiatives to be carried out under the strategy in the financial year, including the following—
  - (i) a description of the initiative;
  - (ii) a forecast of the capital and operating costs for the initiative that the entity reasonably considers will be the likely costs for the year;
  - (iii) the entity's performance targets for the initiative.
- (3) Subsection (2) does not limit the matters that may be included in the plan.
- (4) The distribution entity must, on or before each 30 April in the preceding financial year, give the regulator a copy of the entity's plan for the financial year.

### **127D Approving demand management plan**

The regulator must, on or before 31 May in the preceding financial year—

- (a) approve the distribution entity's demand management plan for the financial year; or
- (b) make recommendations under section 127E(1) to amend the plan.

### **127E Recommendations by regulator**

- (1) Before approving the distribution entity's demand management plan for a financial year, the regulator may—
  - (a) return the plan to the entity; and
  - (b) make recommendations to amend the plan by asking the entity to—
    - (i) consider or further consider any matter; and
    - (ii) amend the plan in the light of its consideration or further consideration.

- (2) The distribution entity must comply with a request under subsection (1)(b).
- (3) If the distribution entity does not implement any or all of the regulator's recommendations, the entity must give the regulator written reasons for not implementing the recommendations.
- (4) The distribution entity must give a copy of the plan to the regulator for approval.
- (5) The plan takes effect as the distribution entity's approved demand management plan for the financial year only when it is approved by the regulator.

#### **127F Amending approved demand management plan**

- (1) The distribution entity may, at any time in a financial year, amend its approved demand management plan for the year.
- (2) However, the plan may be amended only if a change in circumstances happens that indicates the carrying out of a proposed initiative, or the carrying out of a proposed initiative in the way described in the plan, is no longer feasible or practical to achieve the entity's strategy.
- (3) If, in amending the plan, a proposed initiative, or the way a proposed initiative is to be carried out under the plan, is not changed, the entity's performance targets for the proposed initiative must not be changed in the amended plan.
- (4) The distribution entity must give the regulator a copy of the amended plan.
- (5) The plan, as amended, takes effect as the distribution entity's approved demand management plan for the financial year only when it is approved by the regulator.

#### **127G Complying with approved demand management plan**

The distribution entity must use its best endeavours to comply with its approved demand management plan.

## **127H Reporting requirements**

- (1) The distribution entity must, for each financial year, prepare a report comparing details of the following—
  - (a) the proposed initiatives stated in the entity's approved demand management plan for the year;
  - (b) the actual initiatives the entity carried out in the year.
- (2) The distribution entity must give the regulator a copy of the report on or before 31 August in the following financial year.

## **Part 3 Special approvals**

### **128 Approval to connect for generation plant of particular State electricity entities installed immediately before 1 January 1995**

- (1) Ergon Energy has a special approval authorising it to connect the generating plant installed before 1 January 1995 and vested in Capricornia Electricity Corporation, Far North Queensland Electricity Corporation or North Queensland Electricity Corporation as at 1 January 1995 to the transmission grid or supply network to which the generating plant was connected on 1 January 1995.
- (2) Section 27(a) and (c) of the Act applies to Ergon Energy acting under the special approval as if it were a generation entity.

### **129 Approval to connect for mobile generating plant for emergency or maintenance work by distribution entities**

- (1) A distribution entity has a special approval to connect mobile generating plant to its supply network to supply electricity during an emergency or maintenance work on the supply network.
- (2) Section 27(a) and (c) of the Act applies to a distribution entity acting under the special approval as if the supplier were a generation entity.

---

**130 Approval to connect particular generating plant with 30MW or less capacity**

- (1) A person who operates generating plant with a capacity of 30MW or less has a special approval to connect the generating plant to a transmission grid or supply network.
- (2) Section 27(a) and (c) of the Act applies to the person acting under the special approval as if the person were a generation entity.

**131 Special approval holders treated as electricity entities—Act, s 59(2)**

- (1) A special approval holder stated in schedule 3, column 1, is to be treated as an electricity entity for the provisions of the Act stated in schedule 3, column 2, opposite the special approval holder.
- (2) To remove any doubt, it is declared that if a special approval holder is mentioned in more than 1 item in schedule 3, each of the items in which the holder is mentioned applies to the holder.

**132 Special approval for QETC**

QETC has a special approval to generate electricity for a purpose or function mentioned in section 33(2) of the Act.

## **Chapter 5 Prohibited interests**

**133 Distribution authorities**

Holding a retailer authorisation is a prohibited interest for a distribution entity.

## **Chapter 7      Energy efficiency and performance of electrical equipment**

### **Part 1            Minimum energy efficiency and performance**

#### **Division 1        Registration**

##### **138      Application for registration**

- (1) An application for registration of an item of prescribed electrical equipment must be made to the regulator in the approved form, or if there is no approved form, a form acceptable to the regulator.
- (2) The application must be accompanied by each of the following—
  - (a) subject to subsection (7), the prescribed fee;
  - (b) the test results and calculations mentioned in the relevant standard;
  - (c) the other test results mentioned in the relevant standard, in the form for the results set out in the standard;
  - (d) for an item mentioned in schedule 4, part 1—a sample of a label for the item;
  - (e) for an item mentioned in schedule 4, part 3, that is to be labelled—a sample of a label for the item;
  - (f) if required by the regulator, a sample of the equipment;
  - (g) any other relevant information the regulator requires to decide the application.
- (3) The application may specify a range of models of the 1 brand in the same application if each of the models has the same

---

relevant physical characteristics, energy efficiency and performance characteristics.

- (4) If a person other than the applicant signs the application, the application must be accompanied by the applicant's written authority for the person to sign the application.
- (5) If the application is made by electronic communication, subsection (4) is taken to be complied with if—
  - (a) a method is used to identify the applicant and to indicate the applicant's authority; and
  - (b) having regard to all the relevant circumstances when the method was used, the method was as reliable as was appropriate for the purposes for which the authority was communicated; and
  - (c) the regulator consents to the requirement being met by using the method mentioned in paragraph (a).
- (6) The regulator may waive the requirement under subsection (2)(b) and (c).
- (7) If the application is made by electronic communication, the applicant must give the regulator the prescribed fee for the application before the regulator can register the item of prescribed electrical equipment.
- (8) If the application is made by electronic communication, the regulator—
  - (a) may decide the application; but
  - (b) can not register the item the subject of the application until the prescribed fee is paid.

### **139 Requirements for registration**

- (1) The regulator may register an item of prescribed electrical equipment only if the regulator considers—
  - (a) the item complies with section 140; and
  - (b) for equipment mentioned in schedule 4, part 1—the equipment's label complies with section 152; and

- (c) for equipment mentioned in schedule 4, part 3, that is to be labelled—the equipment’s label complies with section 152.
- (2) If the regulator refuses to register the item, the regulator must give the applicant a QCAT information notice about the refusal.

#### **140 Minimum energy efficiency and performance criteria**

- (1) This section states the requirements an item of prescribed electrical equipment must comply with for section 139(1)(a).
- (2) An item of prescribed electrical equipment mentioned in schedule 4, part 1 or 3, must, if tested in accordance with part 1 of the relevant standard, comply with the performance criteria for the item in the relevant standard.
- (3) An item of prescribed electrical equipment mentioned in schedule 4, part 2, must comply with the energy efficiency requirements for the item in the relevant standard.

#### **141 Steps after registration**

- (1) Within 28 days after registering an item of prescribed electrical equipment, the regulator must—
  - (a) fix the item’s maximum registration term; and
  - (b) give the applicant a written notice stating the item’s date of registration and maximum registration term.
- (2) The maximum registration term can not be more than 5 years from the date of registration.
- (3) If the regulator decides to fix the maximum registration term at less than 5 years and the applicant has not agreed to the term, the written notice must include, or be accompanied by, a QCAT information notice about the decision.

---

## **142 Term of registration**

- (1) Registration of an item of prescribed electrical equipment continues in force until the earliest of the following to happen—
  - (a) the end of the item's maximum registration term;
  - (b) the expiry of the relevant standard for the item;
  - (c) the relevant standard for the item is amended and, under the amended standard, the item does not comply with the performance requirements or energy efficiency requirements for the item.
- (2) Subsection (1) is subject to section 149.

## **143 Change of name or address**

- (1) The holder of a registration of an item of prescribed electrical equipment whose name or address changes must, within 14 days after the change, give written notice of it to the regulator.  
Maximum penalty—8 penalty units.
- (2) The regulator must enter details of the new name or address in the register.

## **144 Changing energy efficiency label identifying electrical equipment**

- (1) The holder of a registration of an item of prescribed electrical equipment with an energy efficiency label may apply to the regulator for approval of a change to the label to reflect a change in the way an item of electrical equipment of the type to which the label relates is identified.
- (2) The regulator may approve the change if the application—
  - (a) is made in the approved form; and
  - (b) is accompanied by—
    - (i) subject to subsection (3), the prescribed fee; and
    - (ii) a sample of the changed energy efficiency label.

- (3) If the application is made by electronic communication, the applicant must give the regulator the prescribed fee for the application before the regulator can approve the change.

#### **145 Refusal to change energy efficiency label**

If the regulator refuses to approve a change to an energy efficiency label for which an application is made, the regulator must give the applicant a QCAT information notice about the refusal.

#### **146 Notice of change to energy efficiency label**

Within 28 days after approving a change to an energy efficiency label, the regulator must give written notice of the change to the holder of the label.

#### **146A Request for documents or information confirming compliance with relevant standard**

- (1) This section applies to the holder of a registration of an item of prescribed electrical equipment.
- (2) The regulator may, by written notice given to the holder, require the holder to give the regulator the documents or information that the holder has about whether the item continues to comply with the requirements under section 139 for the registration of the item.
- (3) The notice must state a period of at least 15 business days within which the holder must comply with the requirement.
- (4) The holder must comply with the requirement.

Maximum penalty for subsection (4)—20 penalty units.



- approved testing entity, it does not comply with the relevant standard; or
- (b) the holder of the registration engages in conduct likely to mislead the public about the performance, rating, capacity or the characteristics of the item required by the relevant standard; or
  - (c) the holder gave the regulator false or misleading information about the application for registration, or transfer of registration, of the item; or
  - (d) the holder asks for the cancellation.
- (2) If registration of an item (the *primary item*) of prescribed electrical equipment is cancelled, the regulator may also cancel the registration of any other item of prescribed electrical equipment that the regulator is satisfied—
- (a) has the same relevant physical characteristics, energy efficiency and performance characteristics as the primary item; and
  - (b) was registered on the basis of the same test results as the test results for the primary item.
- (3) If the regulator decides to cancel the registration, the regulator must give the holder a QCAT information notice about the decision.

## **150 Procedure before cancellation**

- (1) If the regulator considers a ground exists to cancel the registration of an item of prescribed electrical equipment, other than at the request of the registration holder, the regulator must, before taking the action, give the holder written notice—
- (a) stating the regulator is considering cancelling the registration; and
  - (b) stating the grounds for the proposed cancellation; and
  - (c) outlining the facts and circumstances forming the basis for the grounds; and

- 
- (d) inviting the holder to show, within a stated time of at least 15 business days, why the registration should not be cancelled.
  - (2) If, after considering all written representations made by the holder within the stated time, the regulator still considers a ground exists to cancel the registration, the regulator may cancel the registration.
  - (3) Cancellation of the registration takes effect on the sixth business day after the holder is given a QCAT information notice under section 149(3).

### **151 Notice, by holder, of cancellation of registration**

- (1) Immediately on receipt of a QCAT information notice about cancellation of the registration of an item of prescribed electrical equipment, the holder of the registration must give written notice of the cancellation to each person to whom the holder has sold an item of the type that was registered.
- (2) Subsection (1) does not require the giving of a notice to a person to whom the type of item had been sold by retail or had been sold at least 1 year before the notice was received.

## **Division 3 Energy efficiency label**

### **152 Energy efficiency label**

- (1) An energy efficiency label for an item of prescribed electrical equipment mentioned in schedule 4, part 1 or 3, must—
  - (a) comply with the labelling requirements of the relevant standard for the item; and
  - (b) not contain any figures, symbols or other words likely to mislead the public about the item's comparative energy consumption, energy efficiency rating or performance characteristics; and
  - (c) if the item is sold—accompany the item.

- (2) If the item is displayed for sale, the energy efficiency label for the item must—
  - (a) be attached to the item—
    - (i) in the way shown in the relevant standard; or
    - (ii) in another way approved by the regulator; and
  - (b) not be attached in a way that it is obscured from view.

*Note—*

See part 3 (Offences) for when equipment must be labelled.

## **Division 4                      Register**

### **153      Register**

- (1) The regulator must keep a register of each item of prescribed electrical equipment registered by the regulator.
- (2) The regulator may enter in the register any particulars contained in an application for registration, or transfer of registration, of the item.
- (3) The register may be kept in a way the regulator considers appropriate.
- (4) The register may form part of a national register.

### **154      Inspection of register**

The regulator must—

- (a) keep the register open for inspection, on payment of the prescribed fee, by members of the public during office hours on business days; and
- (b) on payment of the prescribed fee, give the person a copy of an entry in the register.

---

## **Part 2                      Testing and test reports**

### **Division 1                Preliminary**

#### **155    Testing of prescribed electrical equipment**

- (1) An item of prescribed electrical equipment mentioned in schedule 4, part 1 or 3, must be tested under this part in accordance with part 1 of the relevant standard to find out whether it complies with the performance criteria in the relevant standard.
- (2) An item of prescribed electrical equipment mentioned in schedule 4, part 2, item 1, must be tested under this part to find out whether it complies with the energy efficiency requirements in the relevant standard.
- (3) An item of prescribed electrical equipment mentioned in schedule 4, part 2, item 2, must be tested under this part in accordance with part 102.3 of the relevant standard to find out whether it complies with the minimum energy performance requirements in part 5 of the relevant standard.
- (4) An item of prescribed electrical equipment mentioned in schedule 4, part 2, items 3 to 18, must be tested under this part to find out whether it complies with the minimum energy performance requirements in the relevant standard for the item.
- (5) The testing may be done only by an approved testing entity.

#### **156    Test reports**

- (1) The results of the test must be recorded in a test report.
- (2) The test report must be in the approved form, or if there is no approved form, a form acceptable to the regulator, and contain the following information about the test—
  - (a) the provision of this regulation under which the testing was conducted;

- (b) the name of the entity that conducted the test;
- (c) the date of the test;
- (d) the date of the report;
- (e) the results of the test, in the form set out in the relevant standard;
- (f) other information required to be included in the report under this part.

## **Division 2                      Check testing**

### **157      Requirement by regulator to make available prescribed electrical equipment for testing**

- (1) The regulator may, by written notice given to the holder of the registration of an item of prescribed electrical equipment, require the holder to make an item of the type registered available for the testing (*check testing*) mentioned in section 155.
- (2) The requirement must state—
  - (a) the period, of at least 1 month from the giving of the requirement, within which the item must be made available; and
  - (b) the place where the item is to be made available; and
  - (c) an amount estimated to cover the actual, reasonable cost of the check testing and when it is to be paid to the regulator.
- (3) The holder must make the item available and pay the amount as stated in the requirement.

### **158      What happens if check testing shows noncompliance**

- (1) This section applies if a check test shows that an item of prescribed electrical equipment does not comply with a

performance criteria or energy efficiency requirement of the relevant standard.

- (2) If the actual cost of testing the item is greater than the amount paid under section 157(3) for the check test, the difference may be recovered by the regulator from the holder as a debt owing to the State.
- (3) This section does not affect section 149.

### **159 What happens if check testing shows compliance**

- (1) This section applies if a check test shows that an item of prescribed electrical equipment complies with the performance criteria or energy efficiency requirements of the relevant standard.
- (2) The regulator must refund to the holder the amount paid under section 157(3) for the check test.
- (3) The amount may be recovered by the holder from the regulator as a debt owing by the State to the holder.

### **160 Return of equipment made available to the regulator**

- (1) This section applies if, at the regulator's request, a person makes available to the regulator free of charge an item of prescribed electrical equipment for testing or with an application under this chapter.
- (2) The regulator must give the person written or oral notice that the equipment is available for collection by the person at a stated place as soon as practicable after—
  - (a) for an item made available for testing—
    - (i) if the regulator believes, on reasonable grounds, that the item is required as evidence in a prosecution for an offence—the prosecution and any appeal from the prosecution; or
    - (ii) if subparagraph (i) does not apply—the testing; or

- (b) for an item made available with an application—the regulator decides the application.
- (3) Despite subsection (2)(a)(i), the regulator must give the person written or oral notice immediately after the earlier of the following—
  - (a) the regulator decides the equipment is not required as evidence;
  - (b) a prosecution for an offence involving the type of equipment is not started within 6 months from when the notice would have been given if subsection (2)(a)(i) had not applied.
- (4) If, at the end of 6 months after the notice is given, the equipment has not been collected, the regulator may dispose of the item as the regulator considers appropriate and the person is not entitled to claim for the appliance or any loss or damage to it.

## Part 3                      Offences

### 161      **Part does not apply to second-hand prescribed electrical equipment**

This part does not apply to a second-hand item of prescribed electrical equipment.

### 162      **Prescribed electrical equipment in sch 4, pt 1—labelling and registration**

- (1) A person must not display for sale or sell an item (the *sale item*) of prescribed electrical equipment mentioned in schedule 4, part 1, unless—
  - (a) an item of the same type of prescribed electrical equipment as the sale item (an *alike item*)—
    - (i) is registered under section 139; or

- (ii) was registered under that section at the time when the sale item was manufactured in or imported into the State (the *relevant time*); or
  - (iii) was registered under a corresponding law at the relevant time; and
- (b) an energy efficiency label that complies with section 152 is attached to or accompanies the item in the way required by that section.

Maximum penalty—20 penalty units.

- (2) Subsection (1) does not apply if—
- (a) the sale item is registered under a corresponding law; and
  - (b) an energy efficiency label is attached to or accompanies the sale item and the label complies with, and is attached or accompanies the item, in the way required by the corresponding law.
- (3) Also, subsection (1) does not apply if—
- (a) an alike item was registered under section 139 at the relevant time and—
    - (i) an energy efficiency label is attached to or accompanies the sale item; and
    - (ii) the label complies with section 152 in the way required by the relevant standard as it was in force at that time; or
  - (b) an alike item was registered under a corresponding law at the relevant time and—
    - (i) an energy efficiency label is attached to or accompanies the sale item; and
    - (ii) the label complies with the corresponding law as it was in force at that time; or
  - (c) an alike item was not mentioned in schedule 4, part 1 as it was in force at the relevant time.

**163 Prescribed electrical equipment in sch 4, pt 2—registration**

A person must not sell an item (the *sale item*) of prescribed electrical equipment mentioned in schedule 4, part 2, unless an item of the same type of prescribed electrical equipment as the sale item—

- (a) is registered under section 139; or
- (b) was registered under that section at the time when the sale item was manufactured in or imported into the State (the *relevant time*); or
- (c) was registered under a corresponding law at the relevant time; or
- (d) was not mentioned in schedule 4, part 2 as it was in force at the relevant time.

Maximum penalty—20 penalty units.

**164 Prescribed electrical equipment in sch 4, pt 3—registration**

(1) A person must not sell an item (the *sale item*) of prescribed electrical equipment mentioned in schedule 4, part 3, unless—

- (a) an item of the same type of prescribed electrical equipment as the sale item (an *alike item*)—
  - (i) is registered under section 139; or
  - (ii) was registered under that section at the time when the sale item was manufactured in or imported into the State (the *relevant time*); or
  - (iii) was registered under a corresponding law at the relevant time; and
- (b) if an energy efficiency label is attached to or accompanies the sale item—the label complies with, and is attached to or accompanies the item in the way required by, section 152.

Maximum penalty—20 penalty units.

- 
- (2) Subsection (1) does not apply if—
- (a) the sale item is registered under a corresponding law; and
  - (b) if an energy efficiency label is attached to or accompanies the sale item—the label complies with, and is attached to or accompanies the item in the way required by, the corresponding law.
- (3) Also, subsection (1) does not apply if—
- (a) an alike item was registered under section 139 at the relevant time and any energy efficiency label attached to or accompanying the sale item complies with section 152 in the way required by the relevant standard as it was in force at that time; or
  - (b) an alike item was registered under a corresponding law at the relevant time and any energy efficiency label attached to or accompanying the sale item complies with that law as it was in force at the relevant time; or
  - (c) an alike item was not mentioned in schedule 4, part 3 as it was in force at the relevant time.

## **165 Representations about 3-phase cage induction motors**

A person must not represent that a 3-phase cage induction motor mentioned in schedule 4, part 2, item 2, is a high efficiency motor unless the motor complies with the high efficiency performance requirements for the item in part 5 of the relevant standard.

Maximum penalty—20 penalty units.

## **165A Representations about digital television set-top boxes**

A person must not represent that a digital television set-top box mentioned in schedule 4, part 2, item 6, is a high efficiency set-top box unless it complies with the high efficiency performance requirements for the item in section 3 of the relevant standard.

Maximum penalty—20 penalty units.

### **165B Representations about external power supplies**

A person must not represent that an external power supply mentioned in schedule 4, part 2, item 7, is a high efficiency power supply unless it complies with the high efficiency performance requirements for the item in section 3 of the relevant standard.

Maximum penalty—20 penalty units.

### **166 Marking and labelling particular fluorescent lamp ballasts**

- (1) This section applies to a fluorescent lamp ballast, other than a ballast to which the standard mentioned in schedule 4, part 1, item 6, applies.
- (2) A person must not mark the ballast with an energy efficiency label unless the label—
  - (a) complies with the labelling requirements of the standard mentioned in subsection (1); and
  - (b) is marked on the ballast in the way shown in the standard.

Maximum penalty—20 penalty units.

- (3) If an energy efficiency label is marked on the ballast, a person must not sell the ballast unless it conforms with the energy efficiency rating shown on the label.

Maximum penalty—20 penalty units.

## Chapter 8 Employment in government owned electricity industry

### Part 1 Preliminary

#### 167 Definitions for ch 8

In this chapter—

*employment entitlement*, of an employee, means each of the following—

- (a) the employee's leave entitlement;
- (b) the period of service that would be relevant for working out the redundancy payment to which the employee would be entitled if the employee was made redundant.

*future employer* see section 168(2)(d).

*previous employer* see section 168(2)(a).

*redundancy payment* means a payment made to a person because the person became redundant.

*redundant* see section 168(1).

*redundant employee* see section 168(2).

*State electricity entity* includes an entity declared to be a State electricity entity under section 224.

*suitable alternative employment* see section 169.

#### 168 Meaning of *redundant* and *redundant employee*

- (1) An employee becomes *redundant* if the person's employer no longer needs or has a substantially diminished need for services of a particular kind performed by the person.
- (2) A person is a *redundant employee* if—
  - (a) the person was employed by a State electricity entity (the *previous employer*); and

- (b) the person's employment ended because the person was redundant; and
- (c) the person has received, or is eligible to receive, a redundancy payment from the previous employer; and
- (d) the person has not been offered suitable alternative employment by the previous employer or another State electricity entity (each a *future employer*).

### 169 Meaning of *suitable alternative employment*

- (1) Alternative employment offered to a person by a future employer is *suitable alternative employment* only if the following conditions are satisfied—
  - (a) the person's employment entitlements are continued under the alternative employment;
  - (b) either—
    - (i) the person and the previous employer have agreed the alternative employment is the same or substantially the same as the person's previous employment with the employer; or
    - (ii) the Industrial Relations Commission has decided the alternative employment is the same or substantially the same as the person's previous employment;
  - (c) if, on the offer day, the person is a member of a superannuation scheme and the future employer is a subsidiary of a GOC—
    - (i) the person's membership in the scheme is not affected; and
    - (ii) the employer makes, or agrees to make, the superannuation contributions the employer is required to make for the person to the scheme for the benefit of the person.

(2) Subsection (1)(c) does not apply if the person and future employer enter into an agreement about the superannuation arrangements for the person.

(3) In this section—

*offer day*, for a person to whom alternative employment is offered, means the day the alternative employment is offered to the person.

### 170 Industrial Relations Commission may decide particular matters

If a person and the person's previous employer can not agree, after genuinely attempting to come to an agreement, whether alternative employment offered to the person is the same or substantially the same as the person's previous employment with the employer—

- (a) the person and employer must—
  - (i) treat the disagreement as an industrial dispute; and
  - (ii) immediately give the registrar under the Industrial Relations Act a notice complying with section 229(3) of that Act for the dispute; and
- (b) chapter 7, part 2, of the Industrial Relations Act applies to the disagreement as if—
  - (i) the disagreement were an industrial dispute; and
  - (ii) the notice given under paragraph (a)(ii) were given under section 229(2) of that Act; and
- (c) without limiting section 230(3) and (4) of the Industrial Relations Act, the Industrial Relations Commission may decide whether or not the alternative employment is the same or substantially the same as the person's previous employment.



### 175 Calculation at a proportionate rate for particular employee

- (1) If this chapter provides, for a part-time employee, a quantity or amount (the *proportionate amount*) to be a proportion of another quantity or amount relating to a full-time employee (the *regular amount*), the proportionate amount must be worked out as follows—

$$A = \frac{C}{T} \times R$$

- (2) In subsection (1)—

*work hours* means the period (in hours and, if necessary, a fraction of an hour) for which the part-time employee is scheduled to work.

### 176 Chapter 8 prevails over industrial instruments

If there is any inconsistency between this chapter and the EGTS award or another industrial instrument that applies to electricity industry employees of State electricity entities, this chapter prevails to the extent of the inconsistency.

## Part 3 Transfer of employment within GOE industry

### 177 Application of pt 3

This part applies to a person who transfers employment within the GOE industry (the *transferred employee*).

### 178 When there is transfer of employment within GOE industry

- (1) In this part, a person employed in the GOE industry transfers employment within the GOE industry if the person resigns from employment with a State electricity entity (the *former*

*employer*) to be employed by another State electricity entity (the *new employer*).

- (2) For subsection (1), a person does not resign from employment with a State electricity entity if the person becomes a redundant employee for the entity.
- (3) The transfer is effective when the employee starts employment with the new employer (the *transfer day*).

### **179 When employment with former employer and new employer is taken to be continuous service**

- (1) This section applies if the transfer day is no more than 1 month after the transferred employee ends employment with the former employer.
- (2) To decide employment entitlements of the transferred employee as an employee of the new employer—
  - (a) the employee's continuous service in the GOE industry immediately before ending employment with the former employer is taken to be service continuous with service with the new employer from the transfer day; and
  - (b) the employee's leave entitlement is reduced by leave accrued (or a pro rata amount for leave not yet accrued) during the service and taken or paid for by an employer of the employee.

### **180 Transferred employee may elect for leave entitlement to become leave entitlement with new employer**

- (1) This section applies if the transferred employee is entitled to payment by the former employer of an amount as cash equivalent for accrued leave (or a pro rata amount for leave not yet accrued).
- (2) Before the transfer day, the employee may, by written notice to the former employer, elect for payment not to be made to the employee and, instead, an equivalent amount of leave to be treated as leave accrued by the employee as an employee of

---

the new employer or, for the pro rata amount, as service with the new employer.

- (3) The election may be for all or part of the payment.
- (4) On the making of the election, the former employer must pay the amount stated in the notice not to the employee but to the new employer and give the new employer a certificate of the amount of the leave, or service for which a pro rata amount would have been paid, to which the payment relates.
- (5) The new employer must treat the employee as having accrued the leave or, for the pro rata amount, having the service with the new employer.

### **181 Payment by former employer to new employer towards long service leave entitlements not accrued on transfer**

- (1) This section applies if—
  - (a) at the transfer day, the transferred employee did not have accrued long service leave entitlements; and
  - (b) the employee later accrues a long service leave entitlement by counting service with the former employer as service with the new employer.
- (2) If asked by the new employer, the former employer must pay the new employer an amount for the long service leave entitlements that would have accrued to the former employee because of the employee's service with the former employer had there been no limit on the employee's period of service before the leave entitlement accrued.
- (3) The amount is the amount the employee would have been paid by the former employer if the employee had, immediately before the transfer day, taken the proportion of the leave accrued relating to the service up to the transfer day.

### **182 Transferred employees not made redundant**

A transferred employee is not made redundant merely because of the transfer.

**183 Particular new employers must pay superannuation into transferred employee's existing scheme**

- (1) This section applies if—
  - (a) the new employer is a subsidiary of a GOC; and
  - (b) immediately before the transfer day, the transferred employee was a member of a superannuation scheme (the *employee's existing scheme*).
- (2) However, this section does not apply if the transferred employee and new employer have entered into an agreement about the superannuation arrangements for the employee.
- (3) The new employer must ensure—
  - (a) the transferred employee's membership in the employee's existing scheme is not affected; and
  - (b) the superannuation contributions the employer is required to make for the employee are paid, for the benefit of the employee, into the employee's existing scheme.

**Part 4 Recognition of previous service other than on transfer**

**184 Application of pt 4**

- (1) This part applies to a person who was formerly employed in the GOE industry or the Queensland electricity supply industry within the meaning of the repealed *Electricity Act 1976* (the *former employment*), and is later employed in the GOE industry (the *new employment*), if the person—
  - (a) had been compulsorily retired from the former employment because of ill health, or voluntarily finished employment because of ill health, and the former employer certifies accordingly; or
  - (b) resigned the former employment within 3 months before starting the new employment; or

- (c) is not a redundant employee.
- (2) For subsection (1)(b), an employee finishes employment on the day when all leave entitlements for which the employee was paid a cash equivalent on finishing the employment would have ended if the entitlements had been taken as leave.

## **185 Recognition of previous service**

- (1) The new employer must recognise the period of service of the former employment in working out the period of service in the new employment.
- (2) An employer may recognise, or agree to recognise, previous service of an employee for leave or other purposes only if—
  - (a) this part applies; or
  - (b) the employer is satisfied special circumstances exist in the particular case.
- (3) Subsection (2) is subject to any Act, law or award binding on the employer providing for recognition of the previous service of the employee on conditions more favourable to the employee than the conditions in the subsection.
- (4) An employee in the GOE industry is entitled to any leave or other entitlement accruing because of the recognition of service under this part, but leave or other entitlement availed of, or for which the employee was paid a cash equivalent, must be deducted from the accrued entitlement.
- (5) An appeal does not lie against a decision of the employer about the existence or otherwise of special circumstances under subsection (2)(b).
- (6) The new employer must give the employee a written notice about a decision made under this section.

## Part 5 Long service leave

### Division 1 Entitlement

#### Subdivision 1 General entitlement provision

##### 186 Entitlement to long service leave

- (1) A GOE industry employee is entitled to long service leave under this part if—
  - (a) the employee has at least 10 years continuous service; or
  - (b) the employee resigns because of a domestic or other pressing necessity and has at least 7 years continuous service ending when the person resigns; or
  - (c) the person dies or resigns and has at least 5 years continuous service ending when the person dies or resigns.
- (2) However, subsection (1)(c) applies to an employee who resigns before reaching 55 only if the employee gives to the employer a certificate, from an appropriate doctor, stating the person can not continue in the person's present employment because of the employee's ill health.
- (3) This part does not limit another entitlement to long service leave that the employee may have.
- (4) In this section—

*appropriate doctor* means a doctor who the employer is satisfied has the appropriate expertise to decide whether or not the person is able to continue in the person's present employment.

---

## Subdivision 2 Service and continuity of service

### 187 Service recognised for long service leave purposes

For this part, continuous service for a GOE industry employee means—

- (a) service that is actually continuous or taken to be continuous under section 179; and
- (b) a period of former service that is, under section 185, recognised for working out the period of service of the employee in the GOE industry; and
- (c) for an employee who became a GOE industry employee on 1 January 1995 because of the repealed *Government Owned Corporations (QGC Corporatisation) Regulation 1994* or the repealed *Government Owned Corporations (QTSC Corporatisation) Regulation 1994*—previous service, including broken service, recognised as service for long service leave purposes under the repealed *Electricity Act 1976*.

### 188 Casual employees

- (1) The service of a GOE industry employee with a State electricity entity (the **employer**) who has been employed more than once by 1 or more State electricity entities over a period is continuous service with the employer even though—
  - (a) the employment is broken; or
  - (b) any of the employment is not full-time employment; or
  - (c) the employee is employed by the entity or entities under 2 or more employment contracts; or
  - (d) the employee would, apart from this section, be taken to be engaged in casual employment; or
  - (e) the employee has engaged in other employment during the period.

- (2) However, the continuous service ends if the employment is broken by more than 3 months between the end of 1 employment contract and the start of the next employment contract.
- (3) In working out the length of a the employee's continuous service—
  - (a) service by the employee before 23 June 1990 must not be taken into account; and
  - (b) subject to subsection (2), a period when the employee was not employed by the entity or entities must be taken into account.

### **189 Periods of absence without pay that count as service**

In this part, an employee's absence without pay from employment is counted as the employee's service only if—

- (a) the absence is as sick leave for no more than 3 months; or
- (b) the employee is paid for the absence under the *Workers' Compensation and Rehabilitation Act 2003* for an injury sustained by the employee; or
- (c) the absence is for leave, other than sick leave, of no more than 2 weeks granted by the employer; or
- (d) the employer has approved the inclusion of the period of the absence in the employee's period of service for this part; or
- (e) the employee is a casual employee and section 188 applies.

---

## Subdivision 3 Calculation of entitlement

### 190 Calculation of long service leave

- (1) Long service leave is calculated at the rate of 1.3 weeks on the appropriate pay for each year of the employee's continuous service.
- (2) The appropriate pay is—
  - (a) for a full-time employee—at the full pay rate; and
  - (b) for a part-time employee—at a proportionate amount of full pay rate; and
  - (c) for a casual employee—the hourly rate for ordinary time payable to the employee—
    - (i) if the employee takes the long service leave—on the day the employee starts the leave; or
    - (ii) if the employee's employment is terminated—on the day the termination takes effect.
- (3) The minimum amount payable to a casual employee for long service leave is worked out using the formula—

$$\frac{\text{actual service}}{52} \times \frac{13}{10} \times \text{hourly rate}$$

where—

*actual service* means the total ordinary working hours actually worked by the employee during the employee's period of continuous service.

*hourly rate* means the hourly rate under subsection (2)(c).

### 191 Casual employees—conversion to full-time equivalent

- (1) A State electricity entity may agree with a casual employee that the employee's entitlement to long service leave may be taken in the form of its full-time equivalent.

*Example for subsection (1)—*

If a casual employee—

- (a) is entitled to be paid for 290 hours long service leave; and
- (b) works under an award that provides for a full-time working week of 36.25 ordinary working hours;

the employee and the employer may agree that the employee takes 8 weeks leave ( $290 \div 36.25 = 8$ ).

- (2) This section applies subject to an industrial instrument about the employee's long service leave.

## **Division 2                      Obtaining long service leave**

### **192      Application for long service leave**

An employee who has an entitlement to long service leave and wishes to take long service leave must make written application for the leave to the employer giving timely notice of the wish to start the leave.

### **193      Employer's right to refuse or defer long service leave**

- (1) An employer may refuse an employee's application for long service leave if—
  - (a) timely notice was not given; or
  - (b) the granting of the leave applied for would be unreasonably detrimental to the work of the work unit in which the applicant is employed.
- (2) If the application is refused, the employer must arrange with the employee for the leave applied for to be taken as soon as is mutually convenient.

---

## **Division 3                      Miscellaneous provisions**

### **194      Minimum period**

The minimum period of long service leave that may be granted at a time is 2 weeks.

### **195      Employer's right to recall an employee from leave**

- (1) If special circumstances exist, an employer may cancel long service leave already granted or recall an employee to duty from long service leave.
- (2) If an employer acts under subsection (1), the employee has a discretion—
  - (a) to agree with the employer to take the long service leave, or the balance of long service leave, at a mutually convenient time; or
  - (b) to require the employer to credit the leave or balance of leave to the employee's undrawn long service leave entitlement.

### **196      Public holidays happening during long service leave**

If an employee is entitled under the employee's terms of employment to a particular public holiday and the public holiday happens during a period when the employee is absent on long service leave, a day is added to the employee's period of leave.

### **197      Illness during long service leave**

- (1) This section applies if, for a period of at least 1 week while an employee is on long service leave, the employee could not, if the employee had not been on leave, have performed the employee's normal duties because of illness or injury.

- (2) The employer must approve the granting of sick leave instead of long service leave for the period of the inability to perform normal duties if—
  - (a) the employee makes written application for the leave; and
  - (b) the employee produces a medical certificate from a doctor stating the employee, if the employee had not been on leave, could not have performed the employee's normal duties because of illness or injury; and
  - (c) the entire period mentioned in subsection (1) is covered by the medical certificate produced; and
  - (d) sick leave is available to the employee.
- (3) Subsection (2) may apply to more than 1 period of sick leave if subsection (2) is complied with for each period.
- (4) The period of sick leave granted instead of long service leave under subsection (2) (the *adjusted period*) is the period for which the employee would have been absent on sick leave had the employee not been on long service leave.
- (5) If an employee is granted a period of sick leave under subsection (2)—
  - (a) the day the employee is to resume duties after the long service leave is not affected; and
  - (b) the adjusted period is added to the employee's entitlement to long service leave.
- (6) As soon as practicable after being granted a period of sick leave under subsection (2), the employee may ask the employer for an extension of the period for which the employee is currently absent on long service leave.
- (7) If the employer agrees to the request—
  - (a) the period for which the employee is currently absent on long service leave is extended by the adjusted period; and
  - (b) the employee's entitlement to long service leave is not affected.

- (8) This section applies despite section 189 but subject to section 195.

### **198 Payment of cash equivalent of long service leave**

- (1) This section applies if, on the day an employee's employment ends (the *last day*), the employee is entitled to a period of long service leave.
- (2) The employer must make a payment instead of granting the employee the period of long service leave.
- (3) The amount of the payment is an amount equal to the amount that would have been paid to the employee if the employee had, on the last day, taken all long service leave to which the employee was entitled on the last day.
- (4) If the employee has not died, the employer must pay the amount to the employee on the last day.
- (5) If the employee has died, the employer must pay the amount as soon as is practicable—
  - (a) to the persons (if any) who, the employer is satisfied, are completely or substantially dependent on the earnings of the employee; or
  - (b) in other cases—to the employee's personal representative.

### **199 Preservation of particular existing rights**

- (1) This section applies to an employee (the *affected employee*) who—
  - (a) became a GOE industry employee on 1 January 1995 because of the repealed—
    - (i) *Government Owned Corporations (QGC Corporatisation) Regulation 1994*; or
    - (ii) *Government Owned Corporations (QTSC Corporatisation) Regulation 1994*; and

- (b) under the long service leave arrangements under the repealed *Electricity Act 1976*, would have been entitled—
  - (i) to a greater period of long service leave than the entitlement under this regulation; or
  - (ii) to an amount of cash equivalent of long service leave greater than the amount of cash equivalent of long service leave to which the employee is entitled under this part; or
  - (iii) either to long service leave or to a cash equivalent of long service leave under the arrangements and who is not entitled to long service leave or a cash equivalent of long service leave under this part.
- (2) The affected employee is entitled to be—
  - (a) granted the greater period of long service leave; or
  - (b) paid the amount of cash equivalent of long service leave that is greater in amount; or
  - (c) granted the long service leave or paid the cash equivalent of long service leave to which the employee would have been entitled if the long service leave arrangements had remained in force.
- (3) The granting of long service leave or the payment of a cash equivalent of long service leave under this section is otherwise subject to this part.

## **Part 6                      Locality allowances**

### **200      Application of pt 6**

This part does not apply for a casual employee.

---

**201 Allowance payable to a GOE industry employee with a dependent spouse or dependent child**

- (1) A State electricity entity must pay a locality allowance to its employee who—
  - (a) is stationed at a centre for which a locality allowance is payable under a directive issued under the *Public Service Act 2008*; and
  - (b) proves to the satisfaction of the employer that the employee has a dependent spouse or dependent child.
- (2) The locality allowance is payable—
  - (a) for a full-time employee—at the appropriate rate set out in the directive; and
  - (b) for a part-time employee—at a proportionate amount of the rate payable under paragraph (a).
- (3) Subsection (2) is subject to section 203.
- (4) An employee who is paid the locality allowance must notify the employer immediately an event affecting the entitlement to receive the allowance happens.

**202 Allowance payable to other employees**

- (1) A State electricity entity must pay a locality allowance to its employee (other than an employee who has a dependent spouse or dependent child) who is stationed at a centre for which a locality allowance is payable under a directive issued under the *Public Service Act 2008*.
- (2) The locality allowance is payable—
  - (a) for a full-time employee—at one-half the appropriate rate set out in the directive; and
  - (b) for a part-time employee—at a proportionate amount of the rate payable under paragraph (a).
- (3) If the State electricity entity is satisfied special circumstances exist, the entity may pay the employee a greater locality allowance, not more than the locality allowance payable to an

employee who has a dependent spouse or dependent child stationed at the same centre.

### **203 Allowance payable if both spouses are entitled**

- (1) This section applies to a GOE industry employee who—
  - (a) is entitled to be paid a locality allowance under this part; and
  - (b) has a spouse who—
    - (i) is also entitled to be paid a locality allowance under this part; or
    - (ii) is employed by the State or a State instrumentality and is also entitled to be paid a locality allowance under an Act.
- (2) The locality allowance payable to the GOE employee is as stated in section 202 and not as stated in section 201.
- (3) This section applies whether or not the employee has a dependent child.

### **204 Allowance payable to an employee absent from headquarters on duty**

The locality allowance for a GOE industry employee must not be reduced because the employee is necessarily absent from headquarters overnight on duty and is given free board and accommodation or paid an away from home allowance in place of board and accommodation.

### **205 Allowance payable to an employee on leave**

- (1) The locality allowance for a GOE industry employee must not be reduced because the employee is absent on recreation leave, sick leave or long service leave.
- (2) If the employee is absent on special leave, the employer may pay the allowance to the employee.

- (3) No locality allowance is payable to an employee who is absent on leave without pay.

## **206 Building projects where site allowance is paid**

If a GOE industry employee is stationed at a building project site and is paid a site allowance for employment at the site, the employer must, instead of paying the locality allowance prescribed by this part, pay the employee—

- (a) the divisional allowance or district parity allowance, or both, generally applying at the building project site under awards of the Industrial Relations Commission; and
- (b) the site allowance payable; and
- (c) so much of the locality allowance prescribed by this part (if any) that is more than the total of the amounts under paragraphs (a) and (b).

## **Part 7 Overtime payments**

### **207 Overtime payments**

- (1) This section applies to a GOE industry employee who is employed—
- (a) by an employer declared by the Governor in Council; and
  - (b) for a salary of more than the amount declared by the Governor in Council.
- (2) The working of overtime by the employee, and the rate at which payment for the overtime is paid, is in the employer's discretion.

## **Chapter 9      Internal and external reviews**

### **Part 1            Review of decisions**

#### **208      Who may apply for internal review etc.**

- (1) A person whose interests are affected by a decision mentioned in schedule 5 may apply to QCA for an internal review of the decision.
- (2) A person who seeks an internal review of a decision is entitled to receive a statement of reasons for the decision.

#### **209      Applying for internal review**

- (1) An application by a person for internal review of a decision must be made within 28 days after an information notice about, or other written notice of, the decision is given to the person.
- (2) However, if the notice did not state reasons for the decision and the person asked for a statement of reasons for the decision within the period mentioned in subsection (1), the person may make the application within 28 days after the person is given the statement of reasons.
- (3) In addition, QCA may extend the period for making an application for internal review.
- (4) An application for internal review must be written and state in detail the grounds on which the applicant seeks internal review of the decision.

#### **210      Stay of operation of decision etc.**

- (1) If an application is made under this part for internal review of a decision, the applicant may immediately apply, as provided under the QCAT Act, to QCAT for a stay of the decision.

- 
- (2) QCAT may stay the decision to secure the effectiveness of the internal review or a later application for external review to QCAT.
  - (3) A stay—
    - (a) may be given on conditions QCAT considers appropriate; and
    - (b) operates for the period fixed by QCAT; and
    - (c) may be revoked or amended by QCAT.
  - (4) The period of a stay under this section must not extend past the time when QCA reviews the decision and any later period QCAT allows the applicant to enable the applicant to apply for an external review of QCA's decision.
  - (5) The making of an application under this part for internal review of a decision affects the decision, or the carrying out of the decision, only if the decision is stayed.

## **211 Decision on internal review**

- (1) This section applies to an application under this part for internal review of a decision (the *disputed decision*).
- (2) QCA may confirm the disputed decision, amend the disputed decision or substitute a new decision after considering the applicant's representations.
- (3) QCA must immediately give the applicant written notice of QCA's decision on the application.
- (4) If the decision is not the decision sought by the applicant, the notice must be a QCAT information notice.
- (5) If QCA was not the decision maker and the regulator amends the decision or substitutes a new decision, the amended or substituted decision is, for this regulation (other than this part) taken to be a decision of the decision maker.

## **Part 2                      Appeals and external review**

### **Division 1                      External reviews by QCAT**

#### **212      Who may apply for external review**

The following persons may apply, as provided under the QCAT Act, to QCAT for an external review of the decision mentioned for the person—

- (a) for a decision by QCA under section 88—any party to the dispute;
- (b) for a decision by the regulator or QCA mentioned in schedule 6—a person whose interests are affected by the decision.

### **Division 2                      Appeals about recognition of previous service**

#### **214      Who may appeal**

A person whose interests are affected by a decision under section 185 of the person's employer may appeal against the decision to an Industrial Magistrates Court.

#### **215      Making appeals**

- (1) An appeal under this part must be made within 3 months after written notice for the decision is given to the person.
- (2) However, subsection (3) applies if—
  - (a) the notice under subsection (1) did not state reasons for the decision; and
  - (b) the person asked for a statement of reasons for the decision within the period mentioned in subsection (1).

- (3) The person may make the appeal within 3 months after the person is given the statement of reasons.
- (4) The court may extend the period for making an appeal, even though the time for making the appeal has ended.

## **216 Starting appeals**

- (1) An appeal is started by filing a written notice of appeal with the court.
- (2) A copy of the notice must be served on the decision maker.
- (3) An appeal may be made to the Industrial Magistrates Court nearest the place where the applicant resides or carries on business.

## **217 Stay of operation of decisions**

- (1) A court may grant a stay of the decision to secure the effectiveness of the appeal.
- (2) A stay—
  - (a) may be given on the conditions the court considers appropriate; and
  - (b) operates for the period fixed by the court; and
  - (c) may be revoked or amended by the court.
- (3) The period of a stay under this section must not extend past the time when the court decides the appeal.
- (4) An appeal against a decision affects the decision, or carrying out of the decision, only if the decision is stayed.

## **218 Powers of court on appeal**

- (1) In deciding an appeal, a court—
  - (a) has the same powers as the decision maker; and
  - (b) is not bound by the rules of evidence; and
  - (c) must comply with natural justice; and

- (d) may hear the appeal in court or in chambers.
- (2) An appeal is by way of rehearing.
- (3) The court may—
  - (a) confirm the decision; or
  - (b) set aside the decision and substitute another decision; or
  - (c) set aside the decision and return the issue to the decision maker with the directions the court considers appropriate.

### **219 Effect of court's decision on appeal**

If the court substitutes another decision, the substituted decision is, for this regulation (other than this chapter), taken to be the decision maker's decision.

### **220 Procedure of court**

- (1) The power to make rules of court for an Industrial Magistrates Court under the *Industrial Relations Act 1999* includes power to make rules of court for appeals to the court under this part.
- (2) The procedure for appeal to a court under this part is—
  - (a) in accordance with its rules of court; or
  - (b) in the absence of relevant rules, as directed by an industrial magistrate.
- (3) The court may make any order about costs it considers just.

### **221 Appeals**

An appeal to the Industrial Court from a decision of an Industrial Magistrates Court may be made only on a question of law.

---

## Chapter 10      General provisions

### Part 1                      Application of Judicial Review Act to State electricity entities

#### 222      Commercial and excluded activities for Act, s 256

- (1) For section 256(1), definition *excluded activities*, of the Act, a community service obligation for the charging of customers by a State electricity entity in accordance with price equalisation, or at a price fixed by the Minister, is a prescribed community service obligation.
- (2) For section 256(2) of the Act, negotiations between the Ministers and a State electricity entity about costs and charges for providing electricity as a community service obligation are declared to be commercial activities of the State electricity entity.
- (3) For section 256(2) of the Act, the activities of the System Operator for Queensland are declared to be commercial activities.
- (4) In this section—

***Ministers*** means the Minister who administers the Act and the Minister who administers the *Government Owned Corporations Act 1993*.

***price equalisation*** means a system for charging customers the same price for the supply of electricity, whether or not the cost of the supply is the same.

## **Part 1A                      Distribution network code provisions**

### **Division 1                      Proposals to amend**

#### **222A    Proposal to amend**

- (1) Any person (the *proponent*) may ask QCA to amend a distribution network code in a stated way (the *proposal*).
- (2) However, the proposal may be made only in the way QCA reasonably requires.
- (3) Also, QCA may require the proponent to, in making the proposal, justify how it meets the QCA code objective.

#### **222B    QCA response to proposal**

- (1) This section applies only when any requirements under section 222A relating to the proposal have been complied with.
- (2) QCA must, within 2 months, decide whether or not it will submit the proposal for consultation under division 2.
- (3) If QCA decides to submit the proposal, QCA may submit it in any form it considers appropriate, with or without change.

#### **222C    Notice of decision not to submit for consultation**

If QCA decides not to submit the proposal for consultation under division 2, it must, as soon as practicable after making the decision, give the proponent a written notice stating the decision and its reasons for the decision.

## **222D QCA-initiated amendments not affected**

To remove any doubt, it is declared that this division does not prevent QCA from amending the distribution network code on its own initiative.

## **Division 2 Required consultation for QCA making or amending distribution network code**

### **Subdivision 1 Preliminary**

#### **222E Prescribed consultation—Act, ss 120H(2) and 120PA(1)**

- (1) For sections 120H(2) and 120PA(1) of the Act, the consultation required to be engaged in before QCA may make or amend a distribution network code is any steps as required under subdivisions 2 and 3.
- (2) For subsection (1), the consultation is taken to have been engaged in if the required steps have been substantially carried out or complied with.

#### **222F Application of div 2 for amendments**

- (1) If QCA proposes to amend a distribution network code, this division applies—
  - (a) as if a reference to a proposed distribution network code were a reference to the proposed amendment; and
  - (b) as if a reference to a draft or final version of a proposed code were a reference to the proposed amendment.
- (2) However, QCA may comply with a requirement to publish the proposed amendment by publishing the full distribution network code as amended by the proposed amendment.

## **Subdivision 2      Interim steps**

### **222G    Application of sdiv 2**

This subdivision does not apply if—

- (a) QCA decides the issues for the proposed distribution network code are minor; or
- (b) QCA reasonably considers that it is unnecessary or inappropriate to carry out the steps provided for under this subdivision.

### **222H    Interim consultation notice**

- (1) QCA must—
  - (a) prepare a written notice (the *interim consultation notice*) about the proposed distribution network code; and
  - (b) publish the interim consultation notice on its website; and
  - (c) give the interim consultation notice to anyone it reasonably believes will be interested in the proposed distribution network code.
- (2) The interim consultation notice must state—
  - (a) where a document (the *issues document*) discussing interim issues for the proposed distribution network code may be inspected; and
  - (b) a period (the *interim consultation period*) during which anyone may make written submissions to QCA about the issues.
- (3) The issues document may, but need not be, a draft of the proposed distribution network code.
- (4) The interim consultation period must be a period that is reasonable, having regard to the complexity of the interim issues.

## **222I Submissions**

Anyone may, within the interim consultation period, make a written submission to QCA about the issues mentioned in the issues document.

## **222J Considering submissions**

QCA must, as soon as practicable after the interim consultation period ends, consider all written submissions made under section 222I within that period.

## **222K Release of draft report and draft proposed code**

- (1) QCA must, after complying with section 222J, publish on its website—
  - (a) a draft report about the material issues for the proposed distribution network code; and
  - (b) a draft of the proposed distribution network code.
- (2) The draft of the proposed distribution network code may be a first draft or a revision of any draft of the proposed distribution network code that formed the issues document.

## **Subdivision 3 Final steps**

### **222L Final consultation notice**

- (1) This section applies if subdivision 2 did not apply or if any steps required under the subdivision have been carried out or complied with.
- (2) If subdivision 2 did not apply, QCA must first publish on its website—
  - (a) a draft report about the material issues for the proposed distribution network code; and
  - (b) a draft of the proposed distribution network code.

- (3) QCA must—
  - (a) prepare a written notice (the *final consultation notice*) about the proposed distribution network code; and
  - (b) publish the final consultation notice on its website; and
  - (c) give the final consultation notice to anyone it reasonably believes will be interested in the proposed distribution network code.
- (4) The final consultation notice must state—
  - (a) that QCA has made a draft report about the material issues for the proposed distribution network code and a draft of the proposed distribution network code; and
  - (b) where the drafts may be inspected; and
  - (c) a period (the *final consultation period*) during which anyone may make written submissions to QCA about the drafts.
- (5) The final consultation period must be a period that is reasonable, having regard to the complexity of the drafts.

### **222M Submissions**

Anyone may, within the final consultation period, make a written submission to QCA about the drafts published under section 222L(2).

### **222N Considering submissions**

QCA must, as soon as practicable after the final consultation period ends, consider all written submissions made under section 222M within that period.

### **222O Release of final report and final proposed code**

QCA must, after complying with section 222N, publish on its website—

- (a) a final report about the material issues for the proposed distribution network code; and
- (b) a final version of the proposed distribution network code.

## **Part 2**                      **Declared State electricity entities**

### **224**    **Declarations—Act, s 259A(2)**

- (1) Each of the following entities is declared to be a State electricity entity for the employment conditions, under chapter 8, of its employees—
  - (a) Energy Queensland Limited ACN 612 535 583;
  - (b) SPARQ Solutions Pty Ltd ACN 110 073 400.
- (2) Kogan Creek Power Pty Ltd ACN 088 229 789 is declared to be a State electricity entity for the employment conditions, under sections 167 to 169 and chapter 8, parts 3, 4 and 5, of its employees.
- (3) Energy Queensland Limited ACN 612 535 583 is declared to be a State electricity entity for section 256 of the Act.

## **Part 3**                      **Miscellaneous**

### **225**    **Approved industry superannuation scheme**

On and from 1 July 1995 the Electricity Supply Industry Superannuation Fund (Qld) is an approved industry superannuation scheme.

### **225A Prescribed amount—small photovoltaic generator connected at particular premises**

- (1) This section applies if section 55DBA applies in relation to electricity produced by a photovoltaic system connected at a particular premises to a supply network.
- (2) For the Act, schedule 5, definition *small photovoltaic generator*, paragraph (a), the amount for the photovoltaic system is 30 kilowatts.

### **226 Fees**

- (1) The fees payable to the regulator under the Act are in schedule 7.
- (2) Schedule 8 states the maximum fees payable to an electricity entity for the matters stated in the schedule.
- (3) To remove any doubt, the following is declared for each maximum fee under schedule 8 for a matter—
  - (a) the fee is the maximum amount payable for the matter regardless of whether the fee is charged under the Act, a distribution network code or a contract;
  - (b) the maximum applies to amounts payable by a customer to a retailer or distribution entity or by a retailer to a distribution entity.

### **227 Forms**

The regulator may approve forms for use under the Act.

---

## **Part 4                      Transitional provisions**

### **Division 1                      Transitional provisions for original regulation**

#### **228      Definition for div 1**

In this division—

*1994 regulation* means the expired *Electricity Regulation 1994*.

#### **229      Continuation of agreements for substations**

An agreement under the repealed *Electricity Act 1976*, section 173 or the 1994 regulation, section 57(1) is taken to be an agreement under section 60.

#### **230      Electric lines installed or operated before 1 October 2002**

- (1) This section applies to an electric line installed or operated immediately before 1 October 2002 under section 157 or 157A of the 1994 regulation as in force immediately before that day.
- (2) On and from 1 October 2002, the electric line is taken to have been installed and to be operated under section 21(1) to (3) of the 1994 regulation and section 24(1) to (3) of this regulation.

#### **231      Existing registrations of items of prescribed electrical equipment**

- (1) This section applies to an existing registration in force immediately before 1 September 2006.
- (2) On 1 September 2006, the registration is taken to have been given—
  - (a) under chapter 7; and

(b) despite section 142, for the remainder of its term unless it is cancelled earlier.

(3) In this section—

*existing registration* means a registration, under the 1994 regulation, of an item of prescribed electrical equipment.

### **232 Existing approvals, notices, decisions, directions and requirements under 1994 regulation**

(1) This section applies to an approval, notice, decision, direction or requirement—

(a) given or made by the regulator or an electricity entity (the *relevant entity*) under a provision (the *expired provision*) of chapter 2, 3 or 6 of the 1994 regulation; and

(b) in force immediately before 1 September 2006.

(2) On 1 September 2006, the approval, notice, decision, direction or requirement is taken to have been given or made by the relevant entity, under the provision of this regulation that corresponds, or substantially corresponds, to the expired provision.

### **233 Existing applications**

An application made by a person under chapter 6 of the 1994 regulation and not decided before 1 September 2006, is taken to have been made under chapter 7 of this regulation.

### **234 Unfinished appeals**

An appeal that has been started under the 1994 regulation and not finished before 1 September 2006 continues as if it were an appeal made under chapter 9, part 2, of this regulation.

---

## Division 2                      **Transitional provisions for Electricity Amendment Regulation (No. 3) 2007**

### **235      Small customers for negotiated retail contracts under Act, s 312**

- (1) For section 312 of the Act, chapter 3, part 1A (other than section 30A) applies for deciding who is a small customer as if—
  - (a) that part had commenced on the notification day; and
  - (b) a reference in that part to the FRC day were a reference to the notification day.

- (2) In this section—

*chapter 3, part 1A* means chapter 3, part 1A of this regulation as in force on the FRC day.

*notification day* means the day this section commenced.

### **236      Existing decisions under s 88 or 211**

If, before the FRC day, the regulator had made a decision under section 88 or 211, on the FRC day the decision is taken to have been made by QCA.

### **237      Unfinished referrals and reviews**

- (1) This section applies if—
  - (a) immediately before the FRC day—
    - (i) the regulator had, under section 88, been asked (the *referral*) to decide an issue in dispute; or
    - (ii) an application under section 208 had been made to the regulator for a review of a decision; and
  - (b) the regulator had not made a decision on the issue or review.

- (2) The referral or application is taken to have been made to QCA.
- (3) The regulator must give QCA the referral or application and any documents or information given to the regulator for the referral or review.

### **238 Contestable customers for National Electricity Rules**

For clauses 9.32.1(a)(2) and 9.34.4(b) of the National Electricity Rules, a contestable customer is prescribed to be any customer other than an excluded customer.

## **Division 3 Transitional provision for Electricity Amendment Regulation (No. 4) 2007**

### **239 Provision for new s 142**

- (1) New section 142 applies to an item of prescribed electrical equipment whether the item was registered before or after new section 142 commenced.
- (2) If the item was registered before new section 142 commenced, its maximum registration term is taken to be the term of registration stated in the notice of registration under section 141 as it was in force before the commencement.
- (3) In this section—

*new section 142* means section 142 as replaced under the *Electricity Amendment Regulation (No. 4) 2007*.

---

**Division 4                      Transitional provision for Electricity  
Amendment Regulation (No. 1) 2009**

**240      Demand management plans for 2009 financial year**

- (1) Section 127C(4) applies to a relevant plan as if the reference to each 30 April in the preceding financial year were a reference to 6 July 2009.
- (2) Section 127D applies to a relevant plan as if the reference to 31 May in the preceding financial year were a reference to 6 August 2009.
- (3) In this section—  
*relevant plan* means a distribution entity's demand management plan for the financial year starting on 1 July 2009.

## **Schedule 1            Maximum permitted rating of electric motors**

sections 93 and 94(1)

<b>Locality</b>	<b>Maximum rating</b>
Aurukun	16kW
Badu Island	13kW
Bamaga	46kW
Boigu Island	10kW
Boulia	16kW
Burketown	16kW
Camooweal	16kW
Coconut Island	10kW
Coen	13kW
Darnley Island	8kW
Dauan Island	7kW
Doomadgee	37kW
Gununa	37kW
Hammond Island	5kW
Kowanyama	37kW
Lockhart River	16kW
Mabuiag Island	7kW
Mapoon	12kW
Moa Island (Kubin and St Pauls communities)	10kW

<b>Locality</b>	<b>Maximum rating</b>
Murray Island	13kW
Palm Island	38kW
Pormpuraaw	16kW
Saibai Island	8kW
Stephens Island	4kW
Warraber Island	7kW
Wasaga	37kW
Yam Island	10kW
Yorke Island	10kW

## **Schedule 3            Special approval holders                                  treated as electricity entities**

section 131

<b>Column 1 Special approval holder</b>	<b>Column 2 Provisions of Act</b>
1 the holder of a special approval authorising the holder to provide electricity to a customer	chapter 2, part 2
2 each holder for the time being of special approval no. SA01/07 authorising the operation of an electric line	116A
3 the holder of any special approval	section 120 chapter 5, part 4
4 Essential Energy, under special approval no. SA01/11	section 131A
5 RTA Weipa Pty Ltd, under special approval no. SA18/98	chapter 2, part 9 chapter 4, part 4, divisions 1, 2 and 4 sections 112, 113, 113B and 114 chapter 6

---

## Schedule 4      Prescribed electrical equipment and relevant standards

schedule 9, definitions *prescribed electrical equipment* and *relevant standard*

### Part 1                      Equipment requiring registration and labelling

Prescribed electrical equipment	Relevant standard
1      clothes washing machines	AS/NZS 2040—Performance of household electrical appliances—clothes washing machines, part 1 Methods for measuring performance, energy and water consumption and part 2 Energy efficiency labelling requirements
2      dishwashers	AS/NZS 2007—Performance of household electrical appliances—dishwashers, part 1 Methods for measuring performance, energy and water consumption and part 2 Energy efficiency labelling requirements
3      refrigerating appliances	AS/NZS 4474—Performance of household electrical appliances—refrigerating appliances, part 1 Energy consumption and performance and part 2 Energy labelling and minimum energy performance standard requirements

<b>Prescribed electrical equipment</b>	<b>Relevant standard</b>
4 single-phase non-ducted household air conditioners and heat pumps	AS/NZS 3823—Performance of electrical appliances—Air conditioners and heat pumps, part 2 Energy labelling and minimum energy performance standard (MEPS) requirements
5 rotary clothes dryers	AS/NZS 2442—Performance of household electrical appliances—Rotary clothes dryers, part 1 Energy consumption and performance and part 2 Energy labelling requirements
6 fluorescent lamp ballasts	AS/NZS 4783—Performance of electrical lighting equipment—Ballasts for fluorescent lamps, part 1 Method of measurement to determine energy consumption and performance of ballasts lamp circuits, and part 2 Energy labelling and minimum energy performance standards requirements
7 televisions	AS/NZS 62087—Power consumption of audio, video and related equipment, part 2.2 Minimum energy performance standards (MEPS) and energy rating label requirements for television sets

---

## Part 2                      Equipment requiring registration only

<b>Prescribed electrical equipment</b>	<b>Relevant standard</b>
1     storage water heaters and heat exchange water heaters	AS/NZS 4692—Electric water heaters, part 1 Energy consumption, performance and general requirements and part 2 Minimum energy performance standard (MEPS) requirements and energy labelling
2     3-phase cage induction motors	AS/NZS 1359—Rotating electrical machines—General requirements, part 5 High efficiency and minimum energy performance standards requirements
3     double-capped fluorescent lamps	AS/NZS 4782—Double-capped fluorescent lamps—Performance specifications, part 1 General and part 2 Minimum energy performance standard (MEPS)
4     refrigerated display cabinets	AS 1731—Refrigerated display cabinets, part 1 Terms and definitions and part 14 Minimum energy performance standard (MEPS) requirements
5     power transformers	AS 2374—Power transformers, part 1 General and part 1.2 Minimum energy performance standard (MEPS) requirements for distribution transformers

<b>Prescribed electrical equipment</b>	<b>Relevant standard</b>
6 digital television set-top boxes	AS/NZS 62087—Power consumption of audio, video and related equipment, part 2.1 Minimum energy performance standards (MEPS) requirements for digital television set-top boxes
7 external power supplies	AS/NZS 4665—Performance of external power supplies, part 2 Minimum energy performance standard (MEPS) requirements
8 liquid-chilling packages	AS/NZS 4776—Liquid-chilling packages using the vapour compression cycle, part 2 Minimum energy performance standard (MEPS) and compliance requirements
9 close control air conditioners	AS/NZS 4965—Performance of close control air conditioners, part 2 Minimum energy performance standard (MEPS) requirements
10 incandescent general lighting service lamps	AS 4934.2—Incandescent lamps for general lighting services, part 2 Minimum energy performance standards (MEPS) requirements
11 extra low voltage halogen lamps (non-reflector)	AS 4934.2—Incandescent lamps for general lighting services, part 2 Minimum energy performance standards (MEPS) requirements
12 self-ballasted compact fluorescent lamps (non-reflector)	AS/NZS 4847—Self-ballasted lamps for general lighting services, part 2 Minimum energy performance standards (MEPS) requirements

<b>Prescribed electrical equipment</b>	<b>Relevant standard</b>
13 mains voltage halogen lamps (non-reflector)	AS 4934.2—Incandescent lamps for general lighting services, part 2 Minimum energy performance standards (MEPS) requirements
14 extra low voltage halogen lamps (reflector)	AS 4934.2—Incandescent lamps for general lighting services, Part 2 Minimum energy performance standards (MEPS) requirements
15 candle lamps (>40W)	AS 4934.2—Incandescent lamps for general lighting services, Part 2 Minimum energy performance standards (MEPS) requirements
16 fancy round lamps (>40W)	AS 4934.2—Incandescent lamps for general lighting services, Part 2 Minimum energy performance standards (MEPS) requirements
17 decorative lamps (>40W)	AS 4934.2—Incandescent lamps for general lighting services, Part 2 Minimum energy performance standards (MEPS) requirements
18 transformers and voltage convertors for extra low voltage halogen lamps	AS/NZS 4879.2—Performance of transformers and electronic step-down convertors for ELV lamps—Minimum energy performance standards (MEPS) requirements

## **Part 3**                      **Equipment requiring registration that may be labelled**

<b>Prescribed electrical equipment</b>	<b>Relevant standard</b>
1    single-phase ducted household or commercial air conditioners and heat pumps	AS/NZS 3823—Performance of electrical appliances—Air conditioners and heat pumps, part 2 Energy labelling and minimum energy performance standard (MEPS) requirements
2    single-phase                      non-ducted commercial air conditioners and heat pumps	AS/NZS 3823—Performance of electrical appliances—Air conditioners and heat pumps, part 2 Energy labelling and minimum energy performance standard (MEPS) requirements
3    3-phase                      household                      or commercial air conditioners and heat pumps	AS/NZS 3823—Performance of electrical appliances—Air conditioners and heat pumps, part 2 Energy labelling and minimum energy performance standard (MEPS) requirements

---

**Schedule 5      QCA review of decisions**

section 208

<b>Section</b>	<b>Description of decision</b>
15(1)	facilities electricity entity decides are necessary to attach an overhead service line to the customer's premises or for the entrance, support, protection and termination of an underground service line
36(2)(a)	requirement by distribution entity for customer to regulate the use of an electrical article
36(2)(b)	requirement by distribution entity for customer to use or deal with electricity supplied in the stated way
36(2)(c)	requirement by distribution entity for customer to ensure a motor installation or starting device connected to a source of electricity supply complies with the requirements of the regulator
36(2)(d)	requirement by distribution entity for customer about the power factor of an electrical installation
37	refusal by distribution entity to provide customer connection services to customer's electrical installation
40	decision to require changes to a customer's electrical installation
41	decision to make requirement about provision of links for connecting meters to an incoming electricity supply to a customer's premises
45(2)	decision to make requirement about space, housing, mounting and connecting facilities for a meter or control apparatus for a customer's premises
46(2)	decision to make requirement about provision of safe access to a customer's premises

<b>Section</b>	<b>Description of decision</b>
46(3)	decision to install alternative metering or other equipment on a customer's premises
59(2)	requirement by distribution entity for provision of space for a substation, a right of way or access to the supplier's equipment

---

## **Schedule 6      External reviews of administrative decisions by QCAT**

section 212(b)

<b>Section</b>	<b>Description of decision</b>
24(4)	direction by the regulator to a person to take away an electric line
139(1)	refusal to register an item of prescribed electrical equipment
141(1)(a)	decision to fix a maximum registration term for an item of prescribed electrical equipment of less than 5 years
144	refusal to change an energy efficiency label
147(2)	refusal to approve transfer of registration of item of prescribed electrical equipment
149(1) or (2)	decision to cancel a registration of item of prescribed electrical equipment other than at the request of the holder of the registration
211	decision by QCA on internal review

**Schedule 7      Fees payable to regulator**

section 226(1)

	<b>\$</b>
1    Application for generation authority (Act, s 179)	1,633.70
2    Application for transmission authority (Act, s 188)	1,633.70
3    Application for distribution authority (Act, s 196)	1,633.70
4    Application for special approval (Act, s 209)	477.15
5    Application for transfer of a generation authority, transmission authority, distribution authority or special approval (Act, s 184A, 193A, 201A or 212A)	151.60
6    Application for registration of an item of prescribed electrical equipment (s 138)	210.50
7    Application for approval of a change to an energy efficiency label (s 144)	210.50
8    Application for approval of transfer of registration of an item of prescribed electrical equipment (s 147)	70.10
9    Inspection of the register (s 154)	13.70
10   Copy of 1 entry in the register (s 154)	27.80

## Schedule 8      **Maximum fees payable to electricity entity**

section 226(2)

### Part 1                      **Meter reading and testing**

	\$
1    Special meter reading by Energex	37.10
2    Special meter reading by Ergon Energy	43.10
3    Testing of a meter by a distribution entity	19.95

### Part 2                      **Disconnection and reconnection**

	\$
1    Disconnection of supply of electricity to premises	nil
2    Reconnection of supply of electricity to a customer's (the <i>current customer's</i> ) premises after disconnection at a customer's request or under the National Energy Retail Rules, rule 119(1)(g) to (i)—	
(a) if the reconnection is made during ordinary business hours	nil
(b) if the reconnection is made outside ordinary business hours at the current customer's request	120.90
3    Reconnection of supply of electricity to a customer's premises other than as mentioned in item 2—	
(a) if the reconnection is made during ordinary business hours	50.15

	\$
(b) if the reconnection is made outside ordinary business hours at the customer's request	120.90

### **Part 3 Temporary connections**

	\$
1 Temporary connection of a supply of electricity to a building site by Ergon Energy during ordinary business hours (single-phase or multi-phase)	454.05
2 Temporary connection of a supply of electricity by Energex during ordinary business hours (current transformer or no current transformer)	454.05

### **Part 4 Other services**

	\$
1 Service to a customer conducted by Ergon Energy that is an excluded service, other than a service mentioned in part 1, 2 or 3, if—	
(a) the service is for premises connected to a long rural feeder or an isolated feeder; and	

- (b) QCA has not approved for the service a maximum charge that is stated by QCA to be “price on application”
- \$  
The maximum charge approved by QCA for the service for customers connected to urban feeders

## Schedule 9 Dictionary

### section 3

***actual meter reading*** means an actual meter reading as defined under the metrology procedure made under the National Electricity Rules.

***approved demand management plan***, for chapter 4, part 2, division 2, see section 127A.

***approved form*** means a form approved by the regulator under section 227.

***approved testing entity***, for a test or examination, means—

- (a) a body accredited by the National Association of Testing Authorities, Australia ABN 59 004 379 74 (***NATA***) to perform the test or examination; or
- (b) a body accredited by another body, operating under a reciprocal agreement with NATA, to perform the test or examination; or
- (c) a body approved by the regulator to perform the test or examination.

***AS 60038*** means AS 60038 (Standard voltages) as in force from time to time.

***AS/NZS*** means a joint Standards Australia and Standards New Zealand standard.

***casual employee*** means a GOE industry employee mentioned in section 188.

***category 1 qualifying customer*** see section 30AA(2).

***check testing***, for an item of prescribed electrical equipment, see section 157.

***consumers terminals*** means the point where a customer's electrical installation is connected to the relevant supplier's works.

**consumption** means consumption of electricity.

**corresponding law**, for chapter 7, means 1 of the following laws—

- *Electrical Products Act 2000* (SA)
- *Energy and Utilities Administration Act 1987* (NSW)
- *Electricity Safety Act 1998* (Vic).

**decision maker**, for chapter 9, part 2, division 2, means the entity whose decision is appealed against.

**demand management**, for chapter 4, part 2, division 2, see section 127A.

**demand management plan**, for chapter 4, part 2, division 2, see section 127A.

**EGTS award** see section 171.

**electrical appliance** means an appliance that uses electricity.

**electrical installation** includes part of an electrical installation.

**Electricity Industry Code** means the industry code of that name made by the Minister on 28 June 2007 under section 120B of the Act as in force immediately before the commencement of the *Electricity Competition and Protection Legislation Amendment Act 2014*, section 60.

**electricity industry employee**, for a State electricity entity, means a person—

- (a) who is employed by the entity; and
- (b) whose employment is—
  - (i) in, or relates to, the electricity industry; and
  - (ii) under a classification and salary level or point mentioned in the EGTS award.

**employment entitlement**, for chapter 8, see section 167.

**Energex** means Energex Limited ACN 078 849 055.

**Essential Energy** means Essential Energy established under the *Energy Services Corporations Act 1995* (NSW).

***excluded service*** means a service to a customer by a distribution entity that, under the National Electricity Rules, QCA decides is an excluded service for customers.

***final consultation period***, for chapter 10, part 1A, see section 222L(4)(c).

***former employer***, for chapter 8, part 3, see section 178(1).

***former employment***, for chapter 8, part 4, see section 184(1).

***FRC day*** means the FRC day under section 310 of the Act.

***future employer***, for chapter 8, see section 168(2)(d).

***GOE industry*** means all State electricity entities collectively, including entities declared to be State electricity entities under section 224.

***GOE industry employee***—

- (a) means a person employed by a State electricity entity, including an entity declared to be a State electricity entity under section 224, in a full-time, part-time or casual capacity; and
- (b) includes the chief executive officer of the entity.

***high voltage*** means a voltage of more than 1,000V.

***industrial instrument***, for chapter 8, part 2, see section 171.

***Industrial Relations Act*** means the *Industrial Relations Act 1999*.

***Industrial Relations Commission*** means the Queensland Industrial Relations Commission continued in existence under section 255 of the Industrial Relations Act.

***information notice***, for an action or decision of the regulator or another entity, means a notice stating each of the following—

- (a) the action or decision;
- (b) for an action or decision of the regulator—the reasons for the decision;

- 
- (c) for an action or decision of another entity—that a person who may seek an internal review can ask the entity for a written statement of reasons for the action or decision;
  - (d) the rights of internal review under this regulation;
  - (e) the period in which any internal review under this regulation must be started;
  - (f) how rights of internal review under this regulation are to be exercised.

***interim consultation period***, for chapter 10, part 1A, see section 222H(2)(b).

***isolated feeder*** see the Electricity Industry Code, section 10.1.1.

***issues document*** see section 222H(2)(a).

***jurisdictional regulator*** has the meaning given in the National Electricity Rules.

***locality allowance*** means an allowance payable to an employee stationed in a centre distant from Brisbane to assist in offsetting the disadvantages associated with residence in the centre.

***long rural feeder*** see the Electricity Industry Code, section 10.1.1.

***loss factor*** has the meaning given in the National Electricity Rules.

***low voltage*** means a voltage of no more than 1,000V.

***maximum registration term***, for an item of prescribed electrical equipment, means its maximum registration term fixed under section 141(1)(a).

***new employer***, for chapter 8, part 3, see section 178(1).

***new employment***, for chapter 8, part 4, see section 184(1).

***owner***, for chapter 3, part 1, division 3, see section 58.

***power factor*** has the meaning given in the National Electricity Rules.

***prescribed electrical equipment*** means an item of electrical equipment stated in schedule 4, column 1, as defined in the relevant standard.

***previous employer***, for chapter 8, see section 168(2)(a).

***proponent***, for a proposed amendment of a distribution network code, see section 222A(1).

***proportionate amount***, for chapter 8, see section 175.

***proposal***, for a distribution network code amendment, see section 222A(1).

***proposed transferee***, for prescribed electrical equipment, see section 147.

***redundancy payment***, for chapter 8, see section 167.

***redundant***, for chapter 8, see section 168(1).

***redundant employee***, for chapter 8, see section 168(2).

***register*** means the register the regulator keeps under section 153.

***relevant standard***, for an item of prescribed electrical equipment, means the standard stated in schedule 4 for the equipment item.

***relevant supplier***, for an electrical installation or premises or an electric line, means the distribution entity or the special approval holder who provides customer connection services to the electrical installation or premises or the line.

***responsible person***, for chapter 3, part 1, division 2, see section 39.

***retailer authorisation*** means a retailer authorisation under the NERL (Qld).

***service line*** means an electric line that connects consumers terminals to the relevant supplier's works or the works of another electricity entity.

***special meter reading*** means an actual meter reading that happens at a time other than the time of a scheduled meter reading.

---

***standard control service*** has the meaning given in the National Electricity Rules.

***State electricity entity***, for chapter 8, see section 167.

***strategy***, for chapter 4, part 2, division 2, see section 127C(2)(a).

***suitable alternative employment***, for chapter 8, see section 169.

***supplier*** means a distribution entity or special approval holder who provides customer connection services to an electrical installation or premises.

***supply point***, for a premises, means—

- (a) if the premises is connected to the national grid—the connection point for the premises; or
- (b) if the premises is connected to a supply network that is not part of the national grid—the supply point for the delivery of electricity to the premises.

***transfer day***, for chapter 8, part 3, see section 178(3).

***transferred employee***, for chapter 8, part 3, see section 177.

***urban feeder*** see the Electricity Industry Code, section 10.1.1.

***website***, for the pricing entity, means, if the entity is the Minister, the department's website.

***wiring rules*** means AS/NZS 3000—Electrical installations (known as the Australian/New Zealand Wiring Rules).

## 1 Index to endnotes

- 2 Key
- 3 Table of reprints
- 4 List of legislation
- 5 List of annotations

## 2 Key

### Key to abbreviations in list of legislation and annotations

Key	Explanation	Key	Explanation
AIA	= Acts Interpretation Act 1954	(prev)	= previously
amd	= amended	proc	= proclamation
amd	= amendment	prov	= provision
t			
ch	= chapter	pt	= part
def	= definition	pubd	= published
div	= division	R[X]	= Reprint No. [X]
exp	= expires/expired	RA	= Reprints Act 1992
gaz	= gazette	reloc	= relocated
hdg	= heading	renu	= renumbered
		m	
ins	= inserted	rep	= repealed
lap	= lapsed	(retro	= retrospectively
		)	
notf	= notified	rv	= revised version
d			
num	= numbered	s	= section

<b>Key</b>	<b>Explanation</b>	<b>Key</b>	<b>Explanation</b>
<b>o in c</b>	= order in council	<b>sch</b>	= schedule
<b>om</b>	= omitted	<b>sdiv</b>	= subdivision
<b>orig</b>	= original	<b>SIA</b>	= Statutory Instruments Act 1992
<b>p</b>	= page	<b>SIR</b>	= Statutory Instruments Regulation 2012
<b>para</b>	= paragraph	<b>SL</b>	= subordinate legislation
<b>prec</b>	= preceding	<b>sub</b>	= substituted
<b>pres</b>	= present	<b>unnum</b>	= unnumbered
		<b>m</b>	
<b>prev</b>	= previous		

### 3 Table of reprints

A new reprint of the legislation is prepared by the Office of the Queensland Parliamentary Counsel each time a change to the legislation takes effect.

The notes column for this reprint gives details of any discretionary editorial powers under the **Reprints Act 1992** used by the Office of the Queensland Parliamentary Counsel in preparing it. Section 5(c) and (d) of the Act are not mentioned as they contain mandatory requirements that all amendments be included and all necessary consequential amendments be incorporated, whether of punctuation, numbering or another kind. Further details of the use of any discretionary editorial power noted in the table can be obtained by contacting the Office of the Queensland Parliamentary Counsel by telephone on 3003 9601 or email [legislation.queries@oqpc.qld.gov.au](mailto:legislation.queries@oqpc.qld.gov.au).

From 29 January 2013, all Queensland reprints are dated and authorised by the Parliamentary Counsel. The previous numbering system and distinctions between printed and electronic reprints is not continued with the relevant details for historical reprints included in this table.

<b>Reprint No.</b>	<b>Amendments included</b>	<b>Effective</b>	<b>Notes</b>
1	none	1 September 2006	
1A	2006 SL No. 279	17 November 2006	

<b>Reprint No.</b>	<b>Amendments included</b>	<b>Effective</b>	<b>Notes</b>
1B	2007 SL No. 13	16 February 2007	
1C	2007 SL No. 50	5 April 2007	
1D	2007 SL No. 122	15 June 2007	
2	2007 SL No. 122	1 July 2007	
2A	2007 SL No. 314	7 December 2007	
2B	2008 SL No. 92	18 April 2008	
2C	2008 SL No. 194	27 June 2008	
2D	2008 SL No. 192 2008 SL No. 193 2008 SL No. 209	1 July 2008	R2D withdrawn, see R3
3	—	1 July 2008	
3A	2009 SL No. 83	12 June 2009	
3B	2009 SL No. 73 2009 Act No. 13	1 July 2009	
3C	2009 SL No. 138	3 July 2009	
3D	2009 SL No. 172	1 September 2009	
3E	2009 SL No. 197	1 October 2009	
3F	2009 SL No. 197	1 November 2009	
3G	2009 SL No. 255	13 November 2009	
3H	2009 Act No. 24	1 December 2009	
3I	2009 SL No. 280	18 December 2009	
3J	2009 SL No. 298	1 January 2010	R3J withdrawn, see R4
4	—	1 January 2010	

<b>Reprint No.</b>	<b>Amendments included</b>	<b>Effective</b>	<b>Notes</b>
4A	2010 SL No. 116	1 July 2010	
4B	—	1 September 2010	prov exp 31 August 2010
4C	2010 Act No. 53	1 December 2010	
4D	2010 SL No. 337	3 December 2010	
4E	2010 SL No. 321	1 January 2011	
4F	2011 SL No. 42	15 April 2011	
4G	2011 SL No. 93	1 July 2011	
4H	2011 Act No. 29	13 September 2011	R4H withdrawn, see R5
5	—	13 September 2011	
5A	2011 SL No. 254 2011 SL No. 255	2 December 2011	
5B	2011 SL No. 235	1 January 2012	
5C	2012 SL No. 88	29 June 2012	
5D	2012 SL No. 93 2012 SL No. 94	1 July 2012	
5E	2012 SL No. 99	6 July 2012	
5F	2012 SL No. 211	23 November 2012	
<b>Current as at</b>		<b>Amendments included</b>	<b>Notes</b>
1 July 2013		2013 SL No. 85 2013 SL No. 105	

<b>Current as at</b>	<b>Amendments included</b>	<b>Notes</b>
1 July 2014	2013 SL No. 105 2014 SL No. 94 2014 SL No. 118 2014 SL No. 138	
1 July 2015	2014 SL No. 338 (amd 2015 SL No. 59) 2015 SL No. 59	
20 May 2016	2016 SL No. 51	
30 June 2016	2016 SL No. 100	
1 July 2016	2016 SL No. 93	
1 July 2017	2017 SL No. 74	RA s 35
3 July 2017	2017 SL No. 103	
1 September 2017	2017 SL No. 178	
27 October 2017	2017 SL No. 223	

## **4 List of legislation**

### **Regulatory impact statements**

For subordinate legislation that has a regulatory impact statement, specific reference to the statement is included in this list.

### **Explanatory notes**

All subordinate legislation made on or after 1 January 2011 has an explanatory note. For subordinate legislation made before 1 January 2011 that has an explanatory note, specific reference to the note is included in this list.

### **Electricity Regulation 2006 SL No. 200**

made by the Governor in Council on 10 August 2006  
notfd gaz 11 August 2006 pp 1725–8  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 September 2006 (see s 2)

exp 31 August 2018 (see SIA s 56A(2) and SIR s 3 sch 2 pt 2)  
Notes—(1) The expiry date may have changed since this reprint was published. See the latest reprint of the SIR for any change.  
(2) A regulatory impact statement and explanatory note were prepared. amending legislation—

**Electricity Amendment Regulation (No. 1) 2006 SL No. 279**

notfd gaz 17 November 2006 pp 1321–2  
commenced on date of notification

**Electricity Amendment Regulation (No. 1) 2007 SL No. 13**

notfd gaz 16 February 2007 pp 760–1  
commenced on date of notification

**Electricity Amendment Regulation (No. 2) 2007 SL No. 50**

notfd gaz 5 April 2007 pp 1592–3  
commenced on date of notification  
Note—Two national regulatory impact statements were prepared.

**Electricity Amendment Regulation (No. 3) 2007 SL No. 122**

notfd gaz 15 June 2007 pp 892–5  
ss 1–2, 33 (to the extent it ins ch 10 pt 4 div 2 hdg, s 235) commenced on date of notification (see s 2)  
remaining provisions commenced 1 July 2007 (see s 2, 1994 No. 64 s 310, 2006 No. 60 s 13, 2007 SL No. 15)

**Electricity Amendment Regulation (No. 4) 2007 SL No. 314**

notfd gaz 7 December 2007 pp 1978–82  
commenced on date of notification

**Government Owned Corporations (QPTC Wind-Up) Regulation 2008 SL No. 92 pts 1, 3**

notfd gaz 18 April 2008 pp 2085–8  
ss 1–2 commenced on date of notification  
remaining provisions commenced 18 April 2008 (see s 2)

**Mines and Energy Legislation Amendment Regulation (No. 3) 2008 SL No. 192 pts 1, 3**

notfd gaz 27 June 2008 pp 1268–78  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2008 (see s 2)

**Electricity Amendment Regulation (No. 1) 2008 SL No. 193**

notfd gaz 27 June 2008 pp 1268–78  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2008 (see s 2)

**Electricity Amendment Regulation (No. 2) 2008 SL No. 194**

notfd gaz 27 June 2008 pp 1268–78  
commenced on date of notification

**Public Service Regulation 2008 SL No. 209 ss 1–2, 20 sch 2**

notfd gaz 27 June 2008 pp 1268–78

ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2008 (see s 2)

**Mines and Energy Legislation Amendment Regulation (No. 1) 2009 SL No. 73 ss 1–2(1), pt 3**

notfd gaz 5 June 2009 pp 486–8  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2009 (see s 2(1))

**Electricity Amendment Regulation (No. 1) 2009 SL No. 83**

notfd gaz 12 June 2009 pp 619–21  
commenced on date of notification

**Right to Information Act 2009 No. 13 ss 1–2, 213 sch 5**

date of assent 12 June 2009  
ss 1–2 commenced on date of assent  
remaining provisions commenced 1 July 2009 (2009 SL No. 132)

**Queensland Civil and Administrative Tribunal (Jurisdiction Provisions) Amendment Act 2009 No. 24 ss 1–2, ch 5 pt 21**

date of assent 26 June 2009  
ss 1–2 commenced on date of assent  
remaining provisions commenced 1 December 2009 (2009 SL No. 252)

**Electricity Amendment Regulation (No. 2) 2009 SL No. 138**

notfd gaz 3 July 2009 pp 934–6  
commenced on date of notification  
Note—Three national regulatory impact statements were prepared.

**Electricity Amendment Regulation (No. 3) 2009 SL No. 172**

notfd gaz 28 August 2009 pp 1491–6  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 September 2009 (see s 2)

**Electricity Amendment Regulation (No. 4) 2009 SL No. 197**

notfd gaz 18 September 2009 pp 215–16  
ss 1–2 commenced on date of notification  
pt 2 commenced 1 October 2009 (see s 2(1))  
remaining provisions commenced 1 November 2009 (see s 2(2))  
Note—Three national regulatory impact statements were prepared.

**Electricity Amendment Regulation (No. 5) 2009 SL No. 255**

notfd gaz 13 November 2009 pp 825–6  
commenced on date of notification

**Sustainable Planning Regulation 2009 SL No. 280 ss 1–2, pt 9 div 7**

notfd gaz 27 November 2009 pp 1001–6  
ss 1–2 commenced on date of notification  
remaining provisions commenced 18 December 2009 (see s 2)

**Building and Other Legislation Amendment Regulation (No. 4) 2009 SL No. 298 pts 1, 3**

notfd gaz 11 December 2009 pp 1187–91

ss 1–2 commenced on date of notification  
remaining provisions commenced 1 January 2010 (see s 2)

**Mines and Energy Legislation Amendment Regulation (No. 1) 2010 SL No. 116 ss 1–2(1), ch 2 pt 2**

notfd gaz 18 June 2010 pp 529–35  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2010 (see s 2(1))

**Electricity Amendment Regulation (No. 1) 2010 SL No. 321**

notfd gaz 26 November 2010 pp 810–13  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 January 2011 (see s 2)  
Note—A regulatory impact statement was prepared.

**Water and Other Legislation Amendment Act 2010 No. 53 ss 1, 258 sch 2**

date of assent 1 December 2010  
commenced on date of assent

**Electricity Amendment Regulation (No. 2) 2010 SL No. 337**

notfd gaz 3 December 2010 pp 1003–6  
commenced on date of notification

**Electricity Amendment Regulation (No. 1) 2011 SL No. 42**

notfd gaz 15 April 2011 pp 624–6  
commenced on date of notification

**Energy Legislation Amendment Regulation (No. 1) 2011 SL No. 93 pts 1–2**

notfd gaz 17 June 2011 pp 430–4  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2011 (see s 2)

**Electricity Price Reform Amendment Act 2011 No. 29 s 1, pt 3**

date of assent 13 September 2011  
commenced on date of assent

**Electricity Amendment Regulation (No. 2) 2011 SL No. 235**

notfd gaz 25 November 2011 pp 603–6  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 January 2012 (see s 2)

**Electricity Amendment Regulation (No. 3) 2011 SL No. 254**

notfd gaz 2 December 2011 pp 658–9  
commenced on date of notification

**Electricity Amendment Regulation (No. 4) 2011 SL No. 255**

notfd gaz 2 December 2011 pp 658–9  
commenced on date of notification

**Electricity Amendment Regulation (No. 1) 2012 SL No. 88**

notfd gaz 29 June 2012 pp 704–10  
commenced on date of notification

**Electricity Amendment Regulation (No. 2) 2012 SL No. 93**

notfd gaz 29 June 2012 pp 704–10  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2012 (see s 2)

**Energy Legislation Amendment Regulation (No. 1) 2012 SL No. 94 pts 1–2**

notfd gaz 29 June 2012 pp 704–10  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2012 (see s 2)

**Electricity Amendment Regulation (No. 3) 2012 SL No. 99**

notfd gaz 6 July 2012 pp 759–60  
commenced on date of notification

**Electricity Amendment Regulation (No. 4) 2012 SL No. 211**

notfd gaz 23 November 2012 pp 391–2  
commenced on date of notification

**Energy Legislation Amendment Regulation (No. 1) 2013 SL No. 85 pts 1–2**

notfd gaz 31 May 2013 pp 160–5  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2013 (see s 2)

**Electricity and Another Regulation Amendment Regulation (No. 1) 2013 SL No. 105  
ss 1–2(1)–(2), pt 2**

notfd gaz 21 June 2013 pp 503–7  
ss 1–2 commenced on date of notification  
s 5 commenced 1 July 2013 (see s 2(1))  
ss 4, 6–7 commenced 1 July 2014 (see s 2(2))  
remaining provision commenced on date of notification

**Electricity and Another Regulation Amendment Regulation (No. 1) 2014 SL No. 94  
pts 1–2**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 13 June 2014  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2014 immediately after the Natural  
Resources and Mines Legislation (Fees) Amendment Regulation (No. 1) 2014  
(see s 2)

**Electricity Amendment Regulation (No. 1) 2014 SL No. 118**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 20 June 2014  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2014 (see s 2)

**Energy Legislation Amendment Regulation (No. 1) 2014 SL No. 138 pts 1–2**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 27 June 2014  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2014 (immediately after the  
commencement of the Electricity and Another Regulation Amendment  
Regulation (No. 1) 2013, s 7) (see s 2)

**National Energy Retail Law (Consequential Amendments) Regulation 2014 SL No.  
338 pts 1, 3 (this regulation is amended, see amending legislation below)**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 19 December 2014  
ss 1–2 commenced on date of notification  
ss 36, 37 never commenced and om 2015 SL No. 59 s 10  
remaining provisions commenced 1 July 2015 (see s 2)  
amending legislation—

**Energy Legislation Amendment Regulation (No. 1) 2015 SL No. 59 pts 1, 4 (amends 2014 SL No. 338 above)**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 26 June 2015  
commenced on date of notification

**Energy Legislation Amendment Regulation (No. 1) 2015 SL No. 59 pts 1–2**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 26 June 2015  
ss 1–2 commenced on date of notification  
remaining provisions commenced 1 July 2015 (see s 2)

**Electricity Amendment Regulation (No. 1) 2016 SL No. 51**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 20 May 2016  
commenced on date of notification

**Energy Legislation Amendment Regulation (No. 1) 2016 SL No. 93 pts 1–2**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 24 June 2016  
ss 1–2 commenced on date of notification  
pt 2 commenced 1 July 2016 (see s 2)

**Government Owned Corporations (Energy Consolidation) Regulation 2016 SL No. 100 ss 1, 2(4), pt 8 div 2**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 24 June 2016  
ss 1–2 commenced on date of notification  
pt 8 div 2 commenced 30 June 2016 immediately after pts 5–6 commenced (see s 2(4))

**Electricity and Other Legislation (Fees) Amendment Regulation 2017 SL No. 74**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 26 May 2017  
ss 1–2 commenced on date of notification  
pt 2 commenced 1 July 2017 (see s 2)

**Planning (Consequential) and Other Legislation Amendment Regulation 2017 SL No. 103**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 30 June 2017  
ss 1–2 commenced on date of notification  
pt 10 commenced 3 July 2017 (see s 2)

**Electricity (Regional Feed-in Tariff) Amendment Regulation 2017 SL No. 178**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 1 September 2017  
commenced on date of notification

**Electricity (Voltage Limits) Amendment Regulation 2017 SL No. 223**

notfd <[www.legislation.qld.gov.au](http://www.legislation.qld.gov.au)> 27 October 2017  
commenced on date of notification

## **5 List of annotations**

### **How purposes are to be achieved**

s 5 amd 2014 SL No. 338 s 6

### **CHAPTER 2—TECHNICAL REQUIREMENTS**

#### **Supply at low voltage**

s 11 amd 2017 SL No. 223 s 3

#### **Changes of voltage at customer's consumers terminals**

s 13 amd 2017 SL No. 223 s 4

#### **Service lines on customer's premises—electricity entity's obligations**

s 14 amd 2011 SL No. 255 s 3

#### **Service lines on customer's premises—customer's obligations**

s 15 amd 2011 SL No. 255 s 4

#### **Clearing, lopping and pruning of trees on non-freehold land**

s 17 amd 2009 SL No. 280 s 66; 2017 SL No. 103 s 39

#### **Notice to be given to public entity**

s 18 amd 2009 SL No. 172 s 4

#### **Installation and operation of electric line beyond person's property**

s 24 amd 2009 Act No. 24 s 450

### **PART 4—QUALIFYING CUSTOMERS' SMALL PHOTOVOLTAIC GENERATORS**

pt hdg ins 2012 SL No. 211 s 3

amd 2014 SL No. 338 s 7

#### **Prescribed credit amount for credit for electricity produced by small photovoltaic generators**

s 30AA ins 2012 SL No. 99 s 3

amd 2012 SL No. 211 s 4

sub 2014 SL No. 94 s 4

amd 2014 SL No. 338 s 8

#### **When a qualifying customer stops being entitled to be credited with prescribed credit amount for a category 1 qualifying customer**

s 30AB ins 2012 SL No. 211 s 5

amd 2014 SL No. 94 s 5; 2014 SL No. 338 s 9

#### **Prescribed retail entity**

s 30AC ins 2014 SL No. 94 s 6

om 2014 SL No. 338 s 10

### **CHAPTER 3—ELECTRICITY SUPPLY AND SALE TO CUSTOMERS**

#### **PART 1A—PROVISIONS PRESCRIBING PARTICULAR CUSTOMER TYPES**

pt hdg ins 2007 SL No. 122 s 4

om 2014 SL No. 338 s 11

**Division 1—Small customers**

**div hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Subdivision 1—Preliminary**

**sdiv hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Operation of div 1**

**s 30A** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Definitions for div 1**

**s 30B** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Subdivision 2—Initial classification**

**sdiv hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Premises with existing supply point**

**s 30C** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Premises with new supply point**

**s 30D** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Initial classification subject to reclassification**

**s 30E** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Subdivision 3—Distribution entity-initiated reclassification**

**sdiv hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Power to redecide classification**

**s 30F** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Information notice for particular reclassifications**

**s 30G** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Deferral of particular reclassifications until review expiration day**

**s 30H** ins 2007 SL No. 122 s 4  
amd 2009 Act No. 24 s 451  
om 2014 SL No. 338 s 11

**Subdivision 4—Reclassification by application**

**sdiv hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Who may apply**

s **30I** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Restriction on reapplying**

s **30J** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Making and deciding of application**

s **30K** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Notice of decision**

s **30L** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**When decision takes effect**

s **30M** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Subdivision 5—Provisions for deciding classification**

**sdiv hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Application of sdiv 5**

s **30N** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Consumption threshold for small customer classification**

s **30O** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Reference to consumption data**

s **30P** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Discretion to use estimate if consumption data inaccurate**

s **30Q** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Use of estimate if no consumption data available**

s **30R** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Permitted bases for estimates**

s **30S** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Supply points can not be totalled**

s **30T** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Division 2—Market customers**

**div hdg** ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Operation and application of div 2**

s 30U ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Particular customers who are market customers**

s 30V ins 2007 SL No. 122 s 4  
amd 2008 SL No. 193 s 4; 2009 SL No. 255 s 3; 2012 SL No. 93 s 4  
om 2014 SL No. 338 s 11

**Particular large customers**

s 30W ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Particular customers for changes to a premises**

s 30X ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Particular new customers**

s 30Y ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Particular small customers are not market customers**

s 30Z ins 2007 SL No. 122 s 4  
om 2014 SL No. 338 s 11

**Limits on obligation to provide customer connection services**

s 31 om 2007 SL No. 122 s 5

**Notice if services refused**

s 32 om 2007 SL No. 122 s 5

**Entity may provide services even if no obligation**

s 33 om 2007 SL No. 122 s 5

**When distribution entity may refuse to connect or may disconnect**

s 34 amd 2007 SL No. 122 s 6  
om 2014 SL No. 338 s 12

**Customer's liability for customer connection services**

s 35 om 2007 SL No. 122 s 7

**PART 1—DISTRIBUTION ENTITIES****Division 2—Meter and control apparatus requirements for premises**

div hdg sub 2007 SL No. 122 s 8

**Application of div 2**

s 38 sub 2007 SL No. 122 s 8

**Who is the responsible person**

s 39 sub 2007 SL No. 122 s 8  
amd 2014 SL No. 338 s 13(1)

**Customer to change electrical installation for meter connection**

s 40 sub 2007 SL No. 122 s 8

amd 2014 SL No. 338 s 14

**Customer to provide links connecting meter to incoming supply**

s 41 sub 2007 SL No. 122 s 8

amd 2014 SL No. 338 s 15

**No breaking or interfering with meter seal**

s 42 sub 2007 SL No. 122 s 8

**No breaking or interfering with control apparatus seal**

s 43 sub 2007 SL No. 122 s 8

**Placing meter or control apparatus on customer's premises**

s 44 sub 2007 SL No. 122 s 8

amd 2014 SL No. 338 s 16

**Change of placement if building changes or works**

s 45 sub 2007 SL No. 122 s 8

amd 2014 SL No. 338 s 17

**Customers to provide safe access**

s 46 sub 2007 SL No. 122 s 8

**Customers to provide safe access**

s 47 om 2007 SL No. 122 s 8

**Meter accuracy test at customer's request**

s 48 om 2007 SL No. 122 s 8

**When meter taken to register accurately**

s 49 om 2007 SL No. 122 s 8

**Extent of inaccuracy**

s 50 om 2007 SL No. 122 s 8

**Report about test results**

s 51 om 2007 SL No. 122 s 8

**Refund and adjustment if inaccuracy**

s 52 om 2007 SL No. 122 s 8

**Referral of tested meter to regulator**

s 53 om 2007 SL No. 122 s 8

**Inspection and test after referral**

s 54 om 2007 SL No. 122 s 8

**Refund and adjustment after test under s 54**

s 55 om 2007 SL No. 122 s 8

**Using testing instruments**

s 56 om 2007 SL No. 122 s 8

**Division 4—What is not unfair or unreasonable for large customers**

div hdg amd 2007 SL No. 122 s 9

om 2014 SL No. 338 s 18

**Differing methods of charging**

s 63 amd 2007 SL No. 122 s 10; 2010 SL No. 116 s 7  
om 2014 SL No. 338 s 18

**Negotiated connection contracts**

s 64 sub 2007 SL No. 122 s 11  
om 2014 SL No. 338 s 18

**Differing security**

s 65 amd 2007 SL No. 122 s 12  
om 2014 SL No. 338 s 18

**Different terms and capital contributions that are reasonable**

s 66 amd 2007 SL No. 122 s 13  
om 2014 SL No. 338 s 18

**PART 2—RETAIL ENTITIES**

pt hdg om 2014 SL No. 338 s 19

**Division 1—Obligations of retail entities and customers**

div hdg om 2007 SL No. 122 s 14

**Prescribed circumstances for physical connection to a supply network—Act, s 48D**

s 67 sub 2007 SL No. 122 s 15  
om 2014 SL No. 338 s 19

**Limits on obligation to provide customer retail services**

s 68 om 2007 SL No. 122 s 15

**Notice if services refused**

s 69 om 2007 SL No. 122 s 15

**Entity may supply even if no obligation**

s 70 om 2007 SL No. 122 s 15

**When retail entity is not obliged to provide customer retail services**

s 71 amd 2007 SL No. 122 s 16  
om 2014 SL No. 338 s 19

**Division 2—Obligations of host retail entities and customers**

div hdg om 2007 SL No. 122 s 17

**Division 3—What is not unfair or unreasonable**

div hdg om 2007 SL No. 122 s 17

**PART 3—RETAILER OF LAST RESORT SCHEME**

pt hdg ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Division 1—Preliminary**

div hdg ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Subdivision 1—Application**

sdiv hdg ins 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Application of pt 3**

s 72 sub 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Scheme does not affect contracts under Gas Supply Act 2003**

s 73 sub 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Corporations legislation displacement provision for pt 3**

s 74 sub 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Subdivision 2—Interpretation**

sdiv hdg ins 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Who is an affected customer**

s 75 sub 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Who is the retailer of last resort**

s 76 sub 2007 SL No. 122 s 17

amd 2008 SL No. 194 s 3

sub 2010 SL No. 337 s 3

amd 2011 SL No. 42 s 3

om 2014 SL No. 338 s 20

**Who is a relevant distribution entity**

s 76A ins 2010 SL No. 337 s 3

amd 2011 SL No. 42 s 4

om 2014 SL No. 338 s 20

**Subdivision 3—Administration of scheme**

sdiv hdg ins 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**QCA administers scheme**

s 77 sub 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Division 1A—Retail entities appointed as retailers of last resort**

div 1A (ss 77A–77C) ins 2010 SL No. 337 s 4

om 2014 SL No. 338 s 20

**Division 2—Regulated default retail contract**

div hdg ins 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Subdivision 1—Making of regulated default contract**

sdiv hdg ins 2007 SL No. 122 s 17

om 2014 SL No. 338 s 20

**Default contract on ROLR event**

s 78 sub 2007 SL No. 122 s 17  
amd 2010 SL No. 337 s 5  
om 2014 SL No. 338 s 20

**ROLR contract binds ROLR and affected customer**

s 79 sub 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Ending of customer's liability to defaulting retailer**

s 80 sub 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Subdivision 2—ROLR contract terms for small customers**

**sdiv hdg** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Terms**

s 81 sub 2007 SL No. 122 s 17; 2010 SL No. 337 s 6  
om 2014 SL No. 338 s 20

**Subdivision 3—ROLR contract terms for large customers**

**sdiv hdg** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Application of sdiv 3**

s 82 sub 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**ROLR's standard terms generally apply**

s 83 sub 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Price and charges for customer retail services**

s 84 sub 2007 SL No. 122 s 17  
amd 2008 SL No. 193 s 5; 2010 SL No. 116 s 8; 2013 SL No. 105 s 4  
om 2014 SL No. 338 s 20

**Additional one-off ROLR fee**

s 85 sub 2007 SL No. 122 s 17  
om 2010 SL No. 337 s 7

**Subdivision 4—Other provisions about ROLR contract**

**sdiv hdg** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**ROLR contract does not prevent a negotiated retail contract**

s 86 sub 2007 SL No. 122 s 17  
amd 2009 SL No. 83 s 3  
om 2014 SL No. 338 s 20

**Ending of ROLR contract**

s 87 sub 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Division 3—Facilitation of transfer from defaulting retailer to ROLR**

**div hdg** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Purposes of div 3**

s **87A** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Who is a relevant person**

s **87B** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Things taken to be done**

s **87C** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**ROLR may require information**

s **87D** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Compliance with requirement**

s **87E** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Use of information**

s **87F** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Division 3A—Recovery of amounts paid under the scheme**

**div hdg** ins 2010 SL No. 337 s 8  
om 2014 SL No. 338 s 20

**Subdivision 1—Retailer of last resort**

**sdiv 1 (ss 87FA–87FB)** ins 2010 SL No. 337 s 8  
om 2014 SL No. 338 s 20

**Subdivision 2—Relevant distribution entities**

**sdiv 2 (ss 87FC–87FD)** ins 2010 SL No. 337 s 8  
om 2014 SL No. 338 s 20

**Division 4—Miscellaneous provision**

**div hdg** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Power of QCA to require plans and procedures about scheme**

s **87G** ins 2007 SL No. 122 s 17  
om 2014 SL No. 338 s 20

**Security deposits and amounts prepaid to defaulting retailers**

s **87GA** ins 2010 SL No. 337 s 9  
om 2014 SL No. 338 s 20

**Dispute resolution**

s **88** amd 2007 SL No. 122 s 18; 2009 Act No. 24 s 452; 2010 Act No. 53 s 258 sch 2; 2014 SL No. 338 s 21

**QCA may seek advice or information**

s **89** amd 2007 SL No. 122 s 19

**Parties to maintain secrecy of advice or information**

s **90** amd 2007 SL No. 122 s 20; 2009 Act No. 24 s 453

**PART 5—METERS**

**pt hdg** om 2007 SL No. 122 s 21

**Meters must be read annually**

s **91** om 2007 SL No. 122 s 21

**Restrictions**

s **94** amd 2009 SL No. 172 s 5

**PART 7—PRESCRIBED MATTERS ABOUT NOTIFIED PRICES**

**pt hdg** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Division 1—Required consultation for fixing benchmark retail cost element**

**div hdg** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Subdivision 1—Preliminary**

**sdiv hdg** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Prescribed consultation—Act, s 91G(3)**

s **95** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Subdivision 2—Interim steps**

**sdiv hdg** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Interim consultation notice**

s **96** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Making and publication of submissions**

s **97** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Considering submissions**

s **98** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Release of draft decision material**

s **99** sub 2007 SL No. 122 s 22

om 2011 Act No. 29 s 15

**Subdivision 3—Final steps**

**sdiv hdg** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Final consultation notice**

**s 100** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Making and publication of submissions**

**s 101** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Considering submissions**

**s 102** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Release of final decision material**

**s 103** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Subdivision 4—Actual or estimated consumption of less than 0.2GWh**

**sdiv hdg** om 2007 SL No. 122 s 22

**Division 2—Cost of energy**

**div hdg** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Prescribed methodology for estimating long run marginal cost of energy—Act, s 92(6)**

**s 104** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Required principles for framework**

**s 105** sub 2007 SL No. 122 s 22  
amd 2008 SL No. 193 s 6; 2009 SL No. 83 s 4  
om 2011 Act No. 29 s 15

**Matter the framework must take into account**

**s 106** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Consistency of framework with previous tariff years**

**s 107** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Division 3—Retail costs**

**div hdg** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Prescribed methodology for forming view of likely cost of providing customer retail services—Act, s 94(2)**

**s 108** sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Assumption for provision of customer retail services**

s 109 sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Costs to provide customer retail services**

s 110 sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Provision about changes to retail cost framework**

s 111 sub 2007 SL No. 122 s 22  
om 2011 Act No. 29 s 15

**Customers declared to be contestable customers**

s 112 om 2007 SL No. 122 s 22

**Division 4—Resolving disputes about contestability**

div hdg om 2007 SL No. 122 s 22

**Dispute resolution**

s 113 om 2007 SL No. 122 s 22

**Dispute resolver may seek advice or information**

s 114 om 2007 SL No. 122 s 22

**Parties to maintain secrecy of advice or information**

s 115 om 2007 SL No. 122 s 22

**Decision binding**

s 116 om 2007 SL No. 122 s 22

**Division 5—Metering obligation if customer is contestable for premises**

div hdg om 2007 SL No. 122 s 22

**Customer's metering obligation**

s 117 om 2007 SL No. 122 s 22

**CHAPTER 4—MARKET AND SYSTEM ARRANGEMENTS**

**National Electricity Rules to be followed**

s 118 amd 2014 SL No. 338 s 22

**Network operation not to interfere with Queensland system**

s 119 amd 2014 SL No. 338 s 23

**Dealings to be impartial**

s 121 amd 2007 SL No. 122 s 23

**Reasonable charges for services**

s 123 amd 2007 SL No. 122 s 24

**PART 2—CONDITIONS OF AUTHORITIES AND SPECIAL APPROVALS**

**Division 1—General provisions**

div hdg ins 2009 SL No. 83 s 5

**Separation of distribution and retail sectors**

s 124 amd 2014 SL No. 338 s 24

**Compliance with National Electricity Rules instruments**

s 125 amd 2014 SL No. 338 s 25

**Prescribed statement for residential customer accounts**

s 125A ins 2012 SL No. 88 s 3

sub 2013 SL No. 105 s 5

amd 2014 SL No. 118 s 4

om 2014 SL No. 338 s 26

**Retail authority condition for retailer of last resort scheme**

s 126 sub 2007 SL No. 122 s 25

om 2014 SL No. 338 s 26

**Prescribed special approval holder—Act, s 61B**

s 127 prev s 127 om 2007 SL No. 122 s 25

pres s 127 ins 2008 SL No. 193 s 7

sub 2011 SL No. 42 s 5

amd 2014 SL No. 338 s 27

**Division 2—Demand management plans**

div 2 (ss 127A–127H) ins 2009 SL No. 83 s 6

**Approval to connect particular generating plant with 30MW or less capacity**

s 130 amd 2014 SL No. 338 s 28

**Special approval for QETC**

s 132 amd 2014 SL No. 338 s 29

**Distribution authorities**

s 133 amd 2014 SL No. 338 s 30

**CHAPTER 6—QUEENSLAND GAS SCHEME**

ch hdg amd 2008 SL No. 193 s 7

om 2013 SL No. 105 s 6

**PART 1—GENERAL PROVISIONS**

pt hdg om 2013 SL No. 105 s 6

**Prescribed transmission zones**

s 134 om 2013 SL No. 105 s 6

**Prescribed percentage for annual GEC liability—Act, s 135ELA**

s 134A ins 2011 SL No. 42 s 6

amd 2011 SL No. 235 s 4

om 2013 SL No. 105 s 6

**Prescribed programs**

s 135 amd 2009 SL No. 172 s 6

om 2013 SL No. 105 s 6

**PART 2—MONITORING**

pt 2 (ss 136–137) om 2013 SL No. 105 s 6

**Application for registration**

s 138 amd 2007 SL No. 314 s 3

**Requirements for registration**

s 139 amd 2009 Act No. 24 s 454

**Steps after registration**

s 141 sub 2007 SL No. 314 s 4  
amd 2009 Act No. 24 s 455

**Term of registration**

s 142 sub 2007 SL No. 314 s 4

**Refusal to change energy efficiency label**

s 145 amd 2009 Act No. 24 s 456; 2010 SL No. 116 s 9

**Request for documents or information confirming compliance with relevant standard**

s 146A ins 2007 SL No. 314 s 5

**Transfer of registration**

s 147 amd 2009 Act No. 24 s 457

**Cancellation of registration**

s 149 amd 2007 SL No. 314 s 6; 2009 Act No. 24 s 458

**Procedure before cancellation**

s 150 amd 2009 Act No. 24 s 459

**Notice, by holder, of cancellation of registration**

s 151 amd 2009 Act No. 24 s 460

**Energy efficiency label**

s 152 amd 2007 SL No. 314 s 7

**Testing of prescribed electrical equipment**

s 155 amd 2007 SL No. 314 s 8; 2009 SL No. 138 s 3; 2009 SL No. 197 ss 4, 6; 2010 SL No. 321 s 4

**Test reports**

s 156 amd 2007 SL No. 314 s 9

**Prescribed electrical equipment in sch 4, pt 1—labelling and registration**

s 162 amd 2007 SL No. 314 s 10; 2009 SL No. 172 s 7

**Prescribed electrical equipment in sch 4, pt 2—registration**

s 163 sub 2007 SL No. 314 s 11

**Prescribed electrical equipment in sch 4, pt 3—registration**

s 164 amd 2007 SL No. 314 s 12; 2009 SL No. 172 s 8

**Representations about digital television set-top boxes**

s 165A ins 2009 SL No. 138 s 4

**Representations about external power supplies**

s 165B ins 2009 SL No. 138 s 4

**Marking and labelling particular fluorescent lamp ballasts**

s 166 amd 2009 SL No. 138 s 5

**Further restriction on sale of particular air conditioners**

s 166A ins 2009 SL No. 172 s 9  
amd 2009 SL No. 298 s 7  
exp 31 August 2010 (see s 166A(2))

**Allowance payable to a GOE industry employee with a dependent spouse or dependent child**

s 201 amd 2008 SL No. 209 s 20 sch 2

**Allowance payable to other employees**

s 202 amd 2008 SL No. 209 s 20 sch 2

**CHAPTER 9—INTERNAL AND EXTERNAL REVIEWS**

ch hdg sub 2009 Act No. 24 s 461

**Who may apply for internal review etc.**

s 208 amd 2007 SL No. 122 s 26; 2009 Act No. 24 s 462

**Applying for internal review**

s 209 amd 2007 SL No. 122 s 26; 2009 Act No. 24 s 463

**Stay of operation of decision etc.**

s 210 amd 2007 SL No. 122 s 27; 2009 Act No. 24 s 464

**Decision on internal review**

s 211 amd 2007 SL No. 122 s 28; 2009 Act No. 24 s 465

**PART 2—APPEALS AND EXTERNAL REVIEW**

pt hdg amd 2009 Act No. 24 s 466

**Division 1—External reviews by QCAT**

div hdg sub 2009 Act No. 24 s 467

**Who may apply for external review**

s 212 amd 2007 SL No. 122 s 26  
sub 2009 Act No. 24 s 467

**Making appeals**

s 213 om 2009 Act No. 24 s 467

**Division 2—Appeals about recognition of previous service**

div hdg sub 2009 Act No. 24 s 468

**Who may appeal**

s 214 amd 2007 SL No. 122 s 26; 2007 SL No. 314 s 13; 2009 Act No. 24 s 469

**Making appeals**

s 215 amd 2007 SL No. 122 s 26; 2007 SL No. 314 s 13; 2009 Act No. 24 s 470

**Starting appeals**

s 216 amd 2009 Act No. 24 s 471

**Procedure of court**

s 220 amd 2009 Act No. 24 s 472

**Appeals**

s 221 amd 2009 Act No. 24 s 473

## **CHAPTER 10—GENERAL PROVISIONS**

### **PART 1—APPLICATION OF JUDICIAL REVIEW ACT TO STATE ELECTRICITY ENTITIES**

**pt hdg** amd 2009 Act No. 13 s 213 sch 5

#### **Commercial and excluded activities for Act, s 256**

s 222 amd 2009 Act No. 13 s 213 sch 5

### **PART 1A—DISTRIBUTION NETWORK CODE PROVISIONS**

**pt hdg** ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 31

#### **Division 1—Proposals to amend**

**div hdg** ins 2007 SL No. 122 s 29

##### **Proposal to amend**

s 222A ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 13(1)

##### **QCA response to proposal**

s 222B ins 2007 SL No. 122 s 29

##### **Notice of decision not to submit for consultation**

s 222C ins 2007 SL No. 122 s 29

##### **QCA-initiated amendments not affected**

s 222D ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 13(2)

#### **Division 2—Required consultation for QCA making or amending distribution network code**

**div hdg** ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 32

##### **Subdivision 1—Preliminary**

**sdiv hdg** ins 2007 SL No. 122 s 29

##### **Prescribed consultation—Act, ss 120H(2) and 120PA(1)**

s 222E ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 13(1)

##### **Application of div 2 for amendments**

s 222F ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 13

##### **Subdivision 2—Interim steps**

**sdiv hdg** ins 2007 SL No. 122 s 29

##### **Application of sdiv 2**

s 222G ins 2007 SL No. 122 s 29

amd 2014 SL No. 338 s 13(2)

**Interim consultation notice**

s 222H ins 2007 SL No. 122 s 29  
amd 2014 SL No. 338 s 13(2)

**Submissions**

s 222I ins 2007 SL No. 122 s 29

**Considering submissions**

s 222J ins 2007 SL No. 122 s 29

**Release of draft report and draft proposed code**

s 222K ins 2007 SL No. 122 s 29  
amd 2014 SL No. 338 s 13(2)

**Subdivision 3—Final steps**

sdiv hdg ins 2007 SL No. 122 s 29

**Final consultation notice**

s 222L ins 2007 SL No. 122 s 29  
amd 2014 SL No. 338 s 13(2)

**Submissions**

s 222M ins 2007 SL No. 122 s 29

**Considering submissions**

s 222N ins 2007 SL No. 122 s 29

**Release of final report and final proposed code**

s 222O ins 2007 SL No. 122 s 29  
amd 2014 SL No. 338 s 13(2)

**PART 2—DECLARED STATE ELECTRICITY ENTITIES**

**Declaration—Act, ss 259A(1) and 299**

s 223 om 2008 SL No. 92 s 5

**Declarations—Act, s 259A(2)**

s 224 amd 2006 SL No. 279 s 3; 2016 SL No. 100 s 20

**Prescribed amount—small photovoltaic generator connected at particular premises**

s 225A ins 2017 SL No. 178 s 3

**Fees**

s 226 amd 2007 SL No. 122 s 30; 2014 SL No. 338 s 33

**PART 4—TRANSITIONAL PROVISIONS**

**Division 1—Transitional provisions for original regulation**

div hdg ins 2007 SL No. 122 s 31

**Definition for div 1**

s 228 amd 2007 SL No. 122 s 32

**Electric lines installed or operated before 1 October 2002**

s 230 amd 2009 SL No. 83 s 7

---

**Division 2—Transitional provisions for Electricity Amendment Regulation (No. 3) 2007**

**div hdg** ins 2007 SL No. 122 s 33

**Small customers for negotiated retail contracts under Act, s 312**

**s 235** ins 2007 SL No. 122 s 33

**Existing decisions under s 88 or 211**

**s 236** ins 2007 SL No. 122 s 33

**Unfinished referrals and reviews**

**s 237** ins 2007 SL No. 122 s 33

**Contestable customers for National Electricity Rules**

**s 238** ins 2007 SL No. 122 s 33

amd 2009 SL No. 83 s 8

**Division 3—Transitional provision for Electricity Amendment Regulation (No. 4) 2007**

**div hdg** ins 2007 SL No. 314 s 14

**Provision for new s 142**

**s 239** ins 2007 SL No. 314 s 14

**Division 4—Transitional provision for Electricity Amendment Regulation (No. 1) 2009**

**div 4 (s 240)** ins 2009 SL No. 83 s 9

**SCHEDULE 2—OTHER CONTESTABLE CUSTOMERS**

om 2007 SL No. 122 s 34

**SCHEDULE 3—SPECIAL APPROVAL HOLDERS TREATED AS ELECTRICITY ENTITIES**

amd 2007 SL No. 13 s 3; 2007 SL No. 122 s 35; 2011 SL No. 42 s 7; 2014 SL No. 338 s 34; 2016 SL No. 51 s 3

**SCHEDULE 4—PRESCRIBED ELECTRICAL EQUIPMENT AND RELEVANT STANDARDS**

amd 2007 SL No. 50 s 3; 2009 SL No. 138 s 6; 2009 SL No. 172 s 10; 2009 SL No. 197 ss 5, 7; 2010 SL No. 321 s 5; 2011 SL No. 254 s 3

**SCHEDULE 5—QCA REVIEW OF DECISIONS**

amd 2007 SL No. 122 s 36; 2014 SL No. 338 s 35

**SCHEDULE 6—EXTERNAL REVIEWS OF ADMINISTRATIVE DECISIONS BY QCAT**

amd 2007 SL No. 122 s 37; 2007 SL No. 314 s 15; 2009 Act No. 24 s 474

**SCHEDULE 7—FEES PAYABLE TO REGULATOR**

sub 2007 SL No. 122 s 38; 2008 SL No. 192 s 6; 2009 SL No. 73 s 7; 2010 SL No. 116 s 10; 2011 SL No. 93 s 4; 2012 SL No. 94 s 4; 2013 SL No. 85 s 4

amd 2013 SL No. 105 s 7

sub 2014 SL No. 138 s 4; 2015 SL No. 59 s 4; 2016 SL No. 93 s 4; 2017 SL No. 74 s 4

**SCHEDULE 8—MAXIMUM FEES PAYABLE TO ELECTRICITY ENTITY**

sub 2007 SL No. 122 s 38; 2008 SL No. 194 s 4; 2010 SL No. 116 s 11; 2011 SL No. 93 s 4; 2012 SL No. 94 s 4; 2013 SL No. 85 s 4; 2014 SL No. 138 s 4  
amd 2015 SL No. 59 s 5; 2016 SL No. 93 s 5; 2017 SL No. 74 s 5

**SCHEDULE 9—DICTIONARY**

def *actual meter reading* ins 2008 SL No. 194 s 5  
def *affected customer* sub 2007 SL No. 122 s 39(1)–(2)  
om 2014 SL No. 338 s 38(1)  
def *apportioned amount* ins 2010 SL No. 337 s 10(2)  
amd 2014 SL No. 94 s 7(2)  
om 2014 SL No. 338 s 38(1)  
def *approved demand management plan* ins 2009 SL No. 83 s 10(1)  
def *approved testing entity* ins 2007 SL No. 314 s 16(1)  
def *AS 60038* ins 2017 SL No. 223 s 5  
def *benchmark retail cost index* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 94 s 7(1)  
def *billing cycle* ins 2008 SL No. 194 s 5  
om 2014 SL No. 338 s 38(1)  
def *capital contribution* om 2014 SL No. 338 s 38(1)  
def *category 1 qualifying customer* ins 2014 SL No. 338 s 38(2)  
def *category 1 small customer* ins 2012 SL No. 211 s 6  
amd 2014 SL No. 94 s 7(3)  
om 2014 SL No. 338 s 38(1)  
def *category 2 small customer* ins 2012 SL No. 211 s 6  
om 2014 SL No. 94 s 7(1)  
def *classification* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)  
def *closing day* ins 2010 SL No. 337 s 10(2)  
om 2014 SL No. 338 s 38(1)  
def *competent person* om 2007 SL No. 122 s 39(1)  
def *consumption* ins 2007 SL No. 122 s 39(2)  
def *cooling-off period* om 2007 SL No. 122 s 39(1)  
def *corresponding law* amd 2007 SL No. 314 s 16(2)  
def *defaulting retailer* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)  
def *demand management* ins 2009 SL No. 83 s 10(1)  
def *demand management plan* ins 2009 SL No. 83 s 10(1)  
def *distribution entity* amd 2007 SL No. 122 s 39(3)  
om 2014 SL No. 338 s 38(1)  
def *draft decision material* ins 2007 SL No. 122 s 39(2)  
om 2011 Act No. 29 s 16(1)  
def *Electricity Industry Code* om 2007 SL No. 122 s 39(1)  
ins 2008 SL No. 194 s 5  
sub 2014 SL No. 338 s 38  
def *electricity industry employee* amd 2007 SL No. 122 s 39(4)  
def *Energex* ins 2008 SL No. 194 s 5  
def *ESIE award* om 2007 SL No. 122 s 39(1)  
def *Essential Energy* ins 2011 SL No. 42 s 8

def *excluded service* ins 2008 SL No. 194 s 5  
def *expression of interest* ins 2010 SL No. 337 s 10(2)  
om 2014 SL No. 338 s 38(1)  
def *final consultation period* ins 2007 SL No. 122 s 39(2)  
sub 2011 Act No. 29 s 16  
def *FRC day* ins 2007 SL No. 122 s 39(2)  
def *host retail entity* om 2007 SL No. 122 s 39(1)  
def *information notice* amd 2009 Act No. 24 s 475  
def *insolvency official* om 2014 SL No. 338 s 38(1)  
def *interim consultation period* ins 2007 SL No. 122 s 39(2)  
sub 2011 Act No. 29 s 16  
def *isolated feeder* ins 2008 SL No. 194 s 5  
def *issues document* ins 2007 SL No. 122 s 39(2)  
def *long rural feeder* ins 2008 SL No. 194 s 5  
def *lot* om 2007 SL No. 122 s 39(1)  
def *maximum registration term* ins 2007 SL No. 314 s 16(1)  
def *proponent* ins 2007 SL No. 122 s 39(2)  
amd 2014 SL No. 338 s 13(1)  
def *proposal* ins 2007 SL No. 122 s 39(2)  
amd 2014 SL No. 338 s 13(1)  
def *proposed transferee* amd 2009 SL No. 83 s 10(2)  
def *reclassification application* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)  
def *recovery amount* ins 2010 SL No. 337 s 10(2)  
om 2014 SL No. 338 s 38(1)  
def *registered owner* om 2007 SL No. 122 s 39(1)  
def *relevant distribution entity*, for a ROLR event, ins 2010 SL No. 337 s 10(2)  
om 2014 SL No. 338 s 38(1)  
def *relevant distribution entity*, for ch 3, pt 1A, div 1, sub 2007 SL No. 122 s 39(1)–  
(2)  
om 2014 SL No. 338 s 38(1)  
def *relevant person* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)  
def *relevant retail entity* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)  
def *responsible person* ins 2007 SL No. 122 s 39(2)  
def *retail cost view* ins 2007 SL No. 122 s 39(2)  
om 2011 Act No. 29 s 16(1)  
def *retail entity* om 2014 SL No. 338 s 38(1)  
def *retailer authorisation* ins 2014 SL No. 338 s 38(2)  
def *retailer of last resort* ins 2007 SL No. 122 s 39(2)  
sub 2010 SL No. 337 s 10  
om 2014 SL No. 338 s 38(1)  
def *ROLR* ins 2007 SL No. 122 s 39(2)  
sub 2010 SL No. 337 s 10  
om 2014 SL No. 338 s 38(1)  
def *ROLR contract* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)

def *ROLR event* ins 2007 SL No. 122 s 39(2)  
om 2014 SL No. 338 s 38(1)  
def *scheduled meter reading* ins 2008 SL No. 194 s 5  
om 2014 SL No. 338 s 38(1)  
def *service line* sub 2011 SL No. 255 s 5  
def *single premises* om 2007 SL No. 122 s 39(1)  
def *special meter reading* ins 2008 SL No. 194 s 5  
def *standard control service* ins 2011 SL No. 255 s 5(2)  
def *statutory customer contract* om 2007 SL No. 122 s 39(1)  
def *strategy* ins 2009 SL No. 83 s 10(1)  
def *supply point* ins 2007 SL No. 122 s 39(2)  
def *suspended retail entity* om 2007 SL No. 122 s 39(1)  
def *urban feeder* ins 2008 SL No. 194 s 5  
def *website* ins 2007 SL No. 122 s 39(2)

© State of Queensland 2017